

YAESU FT890/AT (Firmware ROM version 1.21) TX 1,5 to 30 MHz mod

- Verify ROM version with the following sequence:
 - hold A/B + A=B knobs while powering up your transceiver.
 - You'll see the display test followed by your ROM version.
 - (It is possible that the Mod will work for other versions but it has not been tried)
- Disconnect FT890 from all connections.
- Open transceiver as explained in the "OPERATING MANUAL".
- Locate (on the "CONTROL UNIT") jumper point JW 3001 and close it with solder.
- Close transceiver back and reconnect power.
- Push PROC, AGC-F, IPO, ATT while Powering ON.
- Now the display shows two digits numbers and three letters (i.e 13 OFF) Rotate main knob and set the display to "02 ON".
- Now press the PROC button.
- Power OFF and then back ON.

Other settings than "02 ON" are of no interest.

This one gives 100w and automatic antenna tuning between 1.5 and 30 mhz.