

Model 533A-533DM(SERIES 600)-535

Code No. 3200-47

This is a condensed reprint of the roll chart dated October 1 1957, and contains all the older type tubes.

In order to save room on the new chart (Jan. 1, 1958) for new tube data, it was necessary to delete data on older tubes. This older tube data is included here for your use when needed.

NOTE: A Star ★ after P1, P2, P3, and P5 indicates that reading is made on English Scale only.

NOTE: A f in the Bias column indicates Bias should be set at 100 and proper button pressed while Bias dial is rotated until tube strikes.

OAY

0A4	KS-0581-0	100	91	P5★	Short on 2-3
0Y4	BLST JX-3502-0	0	45	P2★	Short on 1-2-5
0Z4	JR-0507-0	0	70	P2★	Plate No. 1
0Z4	JR-0307-0	0	70	P2★	Plate No. 2
1A3	1.5 HT-0201-0	0	0	P1★	
1A4	2.0 JR-0230-0	18	31		750
1A5	1.5 JR-5340-0	38	35	P4	800
1A6	2.0 JR-0250-4	16	0		500
1A6	2.0 JR-4350-2	12	73		200
1A7	1.5 JR-0346-5	0	42		900
1A7	1.5 JR-5643-0	32	73		450
1AB5	1.1 JR-6230-0	0	56	P4	1200
1AC5	1.1 EV-2780-0	28	0		500
1AD4	1.1 DV-4120-0	17	62		1400
1AD5	1.1 EV-2780-0	7	31		750
1AE4	1.1 DX-6210-0	25	45	P4	950
1AF4	1.5 DX-6210-0	21	27	P4	700
1AF5	1.5 DX-6580-0	3	15		600
1AF5	1.5 DX-0100-0	0	0	P1★	Diode Sect.
1AG4	1.1 DV-4120-0	27	48		1000
1AG5	1.1 EW-5120-3	40	0	P5★	Diode Sect.
1AG5	1.1 EW-0300-0	0	50	P1★	Diode Sect.
1AH4	1.1 FT-4120-0	17	0		500
1AJ5	1.1 EW-5120-3	22	73		425
1AJ5	1.1 EW-0300-0	0	40	P1★	Diode Sect.
1AK4	1.1 FT-4120-0	17	0		500
1AK5	1.1 EW-5120-3	40	0	P5★	Diode Sect.
1AK5	1.1 EW-0300-0	0	26	P1★	Diode Sect.
1AX2	1.6 BS-0000-0	0	53	P5★	Cap-P
1B3	1.1 JR-0200-0	0	86	P5★	Cap-P, OK ABOVE DIODES OR CAP-P HOLD DOWN PI AND PRESS P4 FOR READING.
1B4	2.0 JR-0330-0	17	35		800
1B5	2.0 JR-5200-0	24	11	P4	575
1B5	2.0 BY-5400-0	0	30	P1★	Triode Sect.
1B5	2.0 JR-5300-0	0	30	P1★	Diode No. 2
1B7	1.5 JR-0340-5	4	48		1000
1B7	1.5 JR-5640-3	17	24		675
1C3	1.5 DX-8200-0	36	32	P4	760
1C5	1.5 JR-5340-0	35	62	P4	1400
1C6	2.0 JR-0253-4	7	29		725
1C6	2.0 JR-4352-0	30	73		375
1C7	2.0 JR-0346-5	10	48		1000
1C7	2.0 JR-5643-0	28	73		400
1D6	2.0 JR-0340-0	0	31		750
1D7	2.0 JR-0346-5	10	74		175
1D7	2.0 JR-5643-0	32	23		675
1D8	1.5 JR-5346-0	50	44	P4	925
1D8	1.5 JR-5643-0	11	11	P4	575
1D8	1.5 JR-6743-0	0	20	P1★	Diode Sect.
1D8	1.5 DX-6210-0	32	15	P4★	Diode Sect.
1DN5	1.1 HT-0800-0	0	0	P1★	Diode Sect.
1E3	1.5 EV-1800-0	22	81	P4	3000
1E4	1.5 JR-5300-0	0	60	P4	1300
1E6	2.0 JR-0340-0	13	35		800
1E7	2.0 JR-5673-4	11	55	P4	1150
1E7	2.0 JR-4376-5	11	55	P4	1150
1F4	2.0 JR-3240-0	16	62	P4	1400
1F5	2.0 JR-5340-0	12	62	P4	1400
1F6	2.0 JR-0230-0	8	21		650
1F6	2.0 JR-0530-0	0	0	P1★	Diode No. 1
1F6	2.0 JR-0430-0	0	0	P1★	Diode No. 2
1F7	2.0 JR-0360-0	8	21		650
1F7	2.0 JR-0463-0	0	0	P1★	Diode No. 1
1F7	2.0 JR-0563-0	0	0	P1★	Diode No. 2
1G3	1.1 JR-0000-0	0	80	P5★	Cap-P, OK ABOVE DIODES OR CAP-P HOLD DOWN PI AND PRESS P4 FOR READING.
1G4	1.5 JR-5300-0	48	37	P4	825
1G5	2.0 JR-5340-0	28	65	P4	1500
1G6	1.5 JR-5600-0	19	24	P4	675
1G6	1.5 JR-4300-0	19	24	P4	675
1H4	2.0 JR-5300-0	40	42	P4	900
1H5	1.5 JR-0200-0	21	73	P4	275
1H5	1.5 JR-0500-0	0	35	P1★	Diode Sect.
1H6	2.0 JR-6300-0	24	11	P4	575
1H6	2.0 BY-6500-0	0	30	P1★	Diode No. 1
1H6	2.0 JR-6400-0	0	30	P1★	Diode No. 2
1J3	1.1 JR-0000-0	0	53	P5★	Cap-P, OK ABOVE DIODES OR CAP-P HOLD DOWN PI AND PRESS P4 FOR READING.
1J6	2.0 JR-5340-0	46	45	P4	950
1J6	2.0 JR-5600-0	15	48	P4	1000
1J6	2.0 JR-4300-0	15	48	P4	1000
1L4	1.5 HT-6210-0	19	49	P4	1025
1L6	1.5 DX-6251-8	0	35		800
1L6	1.5 DX-8152-6	0	0		500
1LA4	1.5 JR-6230-0	38	35	P4	800
1LA6	1.5 JR-6253-4	0	48		1000
1LA6	1.5 JR-4352-6	14	0		500
1LA6	1.5 JR-6230-0	46	44	P4	925
1LC6	1.5 JR-6234-0	0	31		750
1LC6	1.5 JR-6253-4	10	48		1000

600A-605-605A Tube Testers

10-1-57

IMPORTANT

RETAIN THIS DATA SHEET

3A8	2.5 JR-0340-0	17	31	P4	750	PENT. SECT. SHORT ON CAP-P
3A8	2.5 JR-5600-0	0	0	P4	500	Diode Sect. Short on 3
3A8	2.5 BY-0740-0	0	32	P1★		Diode Sect. Short on 3
Each Section: No shorts for testers having serial numbers above 135-136-, or 138-10000						
3AF4A	3.0 JR-2305-0	36	85	P4	4000	
3AL5	3.0 JR-0703-6	0	78	P1★		Diode No. 1
3AL5	3.0 JR-0205-6	0	78	P1★		Diode No. 2
3AU6	3.0 JR-3567-2	11	76	P4	2300	
3AV6	3.0 JR-3702-5	12	58	P4	1250	Triode Sect.
3AV6	3.0 JR-3602-5	0	26	P1★		Diode No. 1
3AV6	3.0 JR-3502-7	0	26	P1★		Diode No. 2
3B2	3.0 JR-0000-0	0	70	P5★		Cap-P, Short on 3
No shorts for testers having serial numbers above 135-136-, or 138-10000						
3B4	2.5 JV-1730-0	50	69	P4	1700	Short on 3
No shorts for testers having serial numbers above 135-136-, or 138-10000						
3B5	2.5 JR-5340-0	32	65		1500	HOLD DOWN PI AND PRESS P4 FOR READING.
3B7	2.5 BY-6700-0	27	65	P4	1500	Triode No. 1
3B7	2.5 JR-3200-0	27	65	P4	1500	Triode No. 2
3B24	3.0 JR-0000-0	0	90	P5★		Cap-P, Short on 3
3B24	3.0 CR-0000-0	0	90	P5★		Cap-P
3B29	4.3 JR-0000-0	0	93	P5★		Cap-P
3BA6	3.0 JR-3567-2	0	79	P4	2700	
3BC5	3.0 JR-3562-0	0	81	P4	3000	
3BE6	3.0 JR-7562-3	0	35		800	AMPL. SECT. HOLD DOWN PI AND PRESS P4
3BE6	3.0 JR-3602-7	20	90	P4	6500	Osc. Sect.
3BN4	3.0 JR-2503-0	19	88	P4	5000	
3BN6	3.0 JR-2753-6	6	27		700	LIMITER GRID. HOLD DOWN PI AND PRESS P4
3BN6	3.0 JR-6753-2	13	0		500	QUADRATURE GRID. HOLD DOWN PI AND PRESS P4
3BU8	3.0 EV-7821-9	0	15		600	PENT. NO. 1. HOLD DOWN PI AND PRESS P4
3BU8	3.0 EV-7321-6	0	15		600	PENT. NO. 2. HOLD DOWN PI AND PRESS P4
3BY6	3.0 JR-3562-7	12	56	P4	1200	Grid No. 1
3BY6	3.0 JR-7562-3	16	0		500	GRID NO. 1. HOLD DOWN PI AND PRESS P4
3BZ6	3.0 JR-3562-7	13	81	P4	3000	
3C2	3.0 JR-0000-0	0	88	P5★		CAP-P, OK ABOVE DIODES OR CAP-P HOLD DOWN PI AND PRESS P4
3C4	2.5 DX-6210-0	41	56	P4	1200	
3C6	2.5 BY-6500-0	10	53	P4	1100	Triode No. 1
3C6	2.5 JR-4300-0	10	53	P4	1100	Triode No. 2
3CB6	3.0 JR-3562-7	19	75	P4	2200	
3CE5	3.0 JR-3562-0	11	84	P4	3500	
3CF6	3.0 JR-3562-7	11	86	P4	4000	
3CS6	3.0 JR-3562-7	0	0		500	GRID NO. 1. HOLD DOWN PI AND PRESS P4
3CS6	3.0 JR-7562-3	0	31		750	GRID NO. 1. HOLD DOWN PI AND PRESS P4
3CY5	3.0 JR-3562-0	12	85		3500	HOLD DOWN PI AND PRESS P4
3D6	2.5 JR-6230-0	36	74	P4	2100	
3DK6	3.0 JR-3562-7	12	85	P4	4000	
3DT6	3.0 JR-3562-7	23	15	P4	600	Grid No. 1
3DT6	3.0 JR-7562-3	16	0		500	GRID NO. 1. HOLD DOWN PI AND PRESS P4
3E5	2.5 DX-6215-0	28	56	P4	1200	SHORT ON 1. HOLD DOWN PI AND PRESS P4 FOR READING
Short on 1 for testers having serial numbers above 135-136-, or 138-10000						
3E6	3.0 JR-6234-0	15	69	P4	1750	
3LE4	2.5 JR-6230-0	65	53	P4	1100	
3LF4	2.5 JR-6230-0	27	67	P4	1600	
3Q4	3.0 HT-1280-0	15	76	P4	2150	
3Q5	2.5 JR-5340-0	34	70	P4	1800	
3S4	2.5 HT-1280-0	24	65		1500	HOLD DOWN PI AND PRESS P4 FOR READING.
3V4	3.0 DX-6210-0	35	68	P4	1650	
4A6	3.0 JR-5600-0	25	48	P4	1000	Triode No. 1
4A6	3.0 BY-4300-0	25	48	P4	1000	Triode No. 2
4AU6	4.3 JR-3567-2	11	76	P4	2300	
4BA6	4.3 JR-3567-2	0	79	P4	2700	
4BC5	4.3 JR-3562-0	0	81	P4	3000	
4BC8	4.3 EV-7608-9	16	90	P4	6200	Triode No. 1
4BC8	4.3 EV-2103-9	16	90	P4	6200	Triode No. 2
4BE6	4.3 JR-7562-3	0	35		800	AMPL. SECT. HOLD DOWN PI AND PRESS P4
4BE6	4.3 JR-3602-7	20	90	P4	6500	Osc. Sect.
4BN6	4.3 JR-2753-6	6	27		700	LIMITER GRID. HOLD DOWN PI AND PRESS P4
4BN6	4.3 JR-6753-2	13	0		500	QUADRATURE GRID. HOLD DOWN PI AND PRESS P4
4B07A	4.3 EV-7608-9	13	90	P4	6400	Triode No. 1
4B07A	4.3 EV-2103-9	13	90	P4	6400	Triode No. 2
4BS8	4.3 EV-7608-9	19	87	P4	4500	Triode No. 1
4BS8	4.3 EV-2103-9	19	87	P4	4500	Triode No. 2
4BU8	4.3 EV-7821-9	0	15		600	PENT. NO. 1. HOLD DOWN PI AND PRESS P4
4BU8	4.3 EV-7321-6	0	15		600	PENT. NO. 2. HOLD DOWN PI AND PRESS P4
4BX8	4.3 EV-7608-9	30	82	P4	3200	Triode No. 1
4BX8	4.3 EV-2103-9	30	82	P4	3200	Triode No. 2
4BZ7	4.3 EV-7608-9	15	91	P4	6800	Triode No. 1
4BZ7	4.3 EV-2103-9	15	91	P4	6800	Triode No. 2
4BZ8	4.3 EV-7608-9	20	88	P4	5000	Triode No. 1
4BZ8	4.3 EV-2103-9	20	88	P4	5000	Triode No. 2
4CB6	4.3 JR-3562-7	19	75	P4	2200	
4CE5	4.3 JR-3562-0	11	84	P4	3500	
4CY5	4.3 JR-3562-0	12	85		3500	HOLD DOWN PI AND PRESS P4
4DT6	4.3 JR-3562-7	23	15	P4	600	Grid No. 1
4DT6	4.3 JR-7562-3	16	0		500	GRID NO. 1. HOLD DOWN PI AND PRESS P4
6A6	6.0 EV-7160-3	41	81	P4	3000	
5AM8	5.0 EV-2631-9	9	81	P4	3000	Pent. Sect.
5AM8	5.0 EV-0807-0	0	78	P1★		Diode Sect.
5AN8	5.0 EV-8679-1	7	86	P4	4000	Pent. Sect.
5AN8	5.0 EV-2173-6	24	83	P4	3300	Triode Sect.
5AQ5	5.0 HR-3562-0	10	86	P4	4100	
5AS4	5.0 HR-0600-0	0	35	P3★		Plate No. 1
5AS4	5.0 HR-0400-0	0	30	P3★		Plate No. 2
5AS8	5.0 EV-2913-7	11	86	P4	4000	Pent. Sect.
5AS8	5.0 EV-0608-7	0	78	P1★		Diode Sect.
5AT8	5.0 EV-9673-8	12	81	P4	3000	Pent. Sect.
5AT8	5.0 EV-1203-8	20	84	P4	3500	Triode Sect.
5AU4	7.5 HR-0600-0	0	51	P3★		Plate No. 1
5AU4	7.5 HR-0400-0	0	46	P3★		Plate No. 2
5AV8	5.0 EV-6987-0	7	86	P4	4000	Pent. Sect.
5AV8	5.0 EV-2301-0	24	83	P4	3300	Triode Sect.
5AW4	6.3 HR-0600-4	0	47	P3★		Plate No. 1
5AW4	6.3 HR-0400-6	0	42	P3★		Plate No. 2
5AX4	5.0 HR-0600-0	0	22	P3★		

6AL7

6D4

COPYRIGHT 1957 THE HICKON ELECTRICAL INSTRUMENT COMPANY, CLEVELAND, OHIO

Table with columns for part number, value, tolerance, power, and description. Includes handwritten notes like 'No shorts for testers having serial numbers above 135-136- or 138-10000' and 'Use This Setting For Short Check Only'.

6B18

6SR7

6B58

6B38	6.3	EV-0603-0	0	78	P1★	Diode No. 1
6B38	6.3	EV-0102-0	0	78	P1★	Diode No. 2
6B35	6.3	EV-3186-0	0	88	P4	5000
6BK6	6.3	JR-3702-5	0	58	P4	1260	Triode Sect.
6BK6	6.3	JR-0602-5	0	57	P1★	Triode No. 1
6BK6	6.3	JR-0502-7	0	57	P1★	Diode No. 2
6BK7	6.3	EV-7608-9	15	90	P4	6500	Triode No. 1
6BK7	6.3	EV-2103-9	15	90	P4	6500	Triode No. 2
6BL4	6.3	JX-0203-0	0	65	P3★
Selectors: JX-0503-0 for testers having serial numbers above 135-, 136-, or 138-10000							
6BL7	6.3	JX-2103-0	24	88	P4	5000	Triode No. 1
6BL7	6.3	JX-4506-0	24	88	P4	5000	Triode No. 2
6BN4	6.3	JR-2503-0	19	88	P4	5000
6BN6	6.3	JR-2753-6	6	27	700	LIMITER GRID HOLD DOWN P1 AND PRESS P4
6BN6	6.3	JR-6753-2	13	0	500	QUADRATURE GRID HOLD DOWN P1 AND PRESS P4
6BN8	6.3	EV-8709-0	20	73	P4	2000	Triode Sect.
6BN8	6.3	EV-0603-0	0	78	P1★	Diode No. 1
6BN8	6.3	EV-0102-0	0	78	P1★	Diode No. 2
6BQ6	6.3	JR-5047-0	42	87	P4	4500	Cap=P
6BQ7	6.3	EV-7608-0	20	88	P4	5000	Triode No. 1
6BQ7	6.3	EV-2103-0	20	88	P4	5000	Triode No. 2
6BQ7A	6.3	EV-7608-9	13	90	P4	6400	Triode No. 1
6BQ7A	6.3	EV-2103-9	13	90	P4	6400	Triode No. 2
6BR8	6.3	EV-9678-0	7	80	P4	2800	Pent. Sect.
6BR8	6.3	EV-1203-0	12	90	P4	6200	Triode Sect.
6BS8	6.3	EV-7608-9	19	87	P4	4500	Triode No. 1
6BS8	6.3	EV-2103-9	19	87	P4	4500	Triode No. 2
6BT6	6.3	JR-3702-0	12	60	P4	1300	Triode Sect.
6BT6	6.3	JR-3602-0	0	57	P1★	Diode No. 1
6BT6	6.3	JR-3502-0	0	57	P1★	Diode No. 2
6BT8	6.3	EV-8679-0	19	75	P4	2200	Pent. Sect.
6BT8	6.3	EV-0103-0	0	68	P1★	Diode No. 1
6BT8	6.3	EV-0203-0	0	68	P1★	Diode No. 2
6BU6	6.3	JR-3702-0	28	65	P4	1500	Triode Sect.
6BU6	6.3	JR-3602-0	0	50	P1★	Diode No. 1
6BU6	6.3	JR-3502-0	0	50	P1★	Diode No. 2
6BU8	6.3	EV-7821-9	0	15	600	PENT. NO. 1, HOLD DOWN P1 AND PRESS P4
6BU8	6.3	EV-7321-6	0	15	600	PENT. NO. 2, HOLD DOWN P1 AND PRESS P4
6BV8	6.3	EV-2301-0	21	89	P4	5600	Triode Sect.
6BV8	6.3	EV-0907-0	0	78	P1★	Diode No. 1
6BV8	6.3	EV-0608-0	0	78	P1★	Diode No. 2
6BW4	6.3	EV-0709-1	0	20	P3★	Plate No. 1
6BW4	6.3	EV-0109-7	0	20	P3★	Plate No. 2
6BW8	6.3	EV-6987-0	7	80	P4	2800	Pent. Sect.
6BW8	6.3	EV-0302-0	0	77	P1★	Diode No. 1
6BW8	6.3	EV-0102-0	0	77	P1★	Diode No. 2
6BX6	6.3	EV-2781-9	10	86	P4	4200
6BX7	6.3	JX-4506-1	33	92	P4	7600	Triode No. 1
6BX7	6.3	JX-2103-5	33	92	P4	7600	Triode No. 2
6BX8	6.3	EV-7608-9	30	82	P4	3200	Triode No. 1
6BX8	6.3	EV-2103-9	30	82	P4	3200	Triode No. 2
6BY5	6.3	JR-0507-0	0	50	P3★	Plate No. 1
6BY5	6.3	JR-0402-0	0	50	P3★	Plate No. 2
6BY6	6.3	JR-3562-7	12	56	P4	1200	Grid No. 1
6BY6	6.3	JR-7562-3	16	0	500	GRID NO. 1, HOLD DOWN P1 AND PRESS P4
6BY8	6.3	EV-1789-2	11	76	P4	2300	Pent. Sect.
6BY8	6.3	EV-0603-0	0	78	P1★	Diode Sect.
6BZ6	6.3	JR-3562-7	13	81	P4	3000
6BZ7	6.3	EV-7608-9	15	91	P4	6800	Triode No. 1
6BZ7	6.3	EV-2103-9	15	91	P4	6800	Triode No. 2
6BZ8	6.3	EV-7608-9	20	88	P4	5000	Triode No. 1
6BZ8	6.3	EV-2103-9	20	88	P4	5000	Triode No. 2
6C4	6.3	JR-6307-0	25	75	P4	2200
6C5	6.3	JR-5307-0	23	73	P4	2000
6C6	6.3	JR-0235-4	20	57	P4	1225	Cap=G
6C7	6.3	JR-0206-0	24	58	P4	1250	Triode Sect. Cap=G
6C7	6.3	JR-0506-0	0	30	P1★	Diode No. 1
6C7	6.3	JR-0406-0	0	30	P1★	Diode No. 2
6C8	6.3	JR-5607-0	20	48	P4	1000	Triode No. 1
6C8	6.3	JR-0304-0	20	48	P4	1000	Triode No. 2
6CA5	6.3	JR-2763-0	20	89	P4	5500	TRIODE NO. 2, CAP-G
6CA7	6.3	JR-5347-2	23	90	P4	6000
6CB5	7.5	JR-4023-0	40	92	P4	7000	Cap=P
6CB6	6.3	JR-3562-7	19	75	P4	2200
6CD6	6.3	JR-5073-0	35	90	P4	6500	Cap=P
6CE5	6.3	JR-3562-0	11	84	P4	3500
6CF6	6.3	JR-3562-7	11	86	P4	4000
6CG7	6.3	EV-7608-9	23	79	P4	2600	Triode No. 1
6CG7	6.3	EV-2103-9	23	79	P4	2600	Triode No. 2
6CG8	6.3	EV-9678-0	12	81	P4	3000	Pent. Sect.
6CG8	6.3	EV-1203-0	20	84	P4	3500	Triode Sect.
6CH7	6.3	EV-7608-0	15	91	P4	6800	Triode No. 1
6CH7	6.3	EV-2103-0	15	91	P4	6800	Triode No. 2
6CH8	6.3	EV-7236-0	7	86	P4	4000	Pent. Sect.
6CH8	6.3	EV-8901-0	24	83	P4	3300	Triode Sect.
6CJ6	6.3	EV-2073-1	51	87	P4	4600	Cap=P
6CK6	6.3	EV-2713-6	0	91	P4	7000
6CL6	6.3	EV-2631-7	0	90	P4	6000
6CL8	6.3	EV-9678-0	10	84	P4	3500	Tetrode Sect.
6CL8	6.3	EV-1203-0	12	89	P4	6000	Triode Sect.
6CM6	6.3	EV-3917-0	13	86	P4	4100
6CM7	6.3	EV-7603-0	27	73	P4	2000	Triode No. 1
6CM7	6.3	EV-8109-0	24	87	P4	4400	Triode No. 2
6CM8	6.3	EV-2673-0	11	84	P4	3500	Pent. Sect.
6CM8	6.3	EV-9108-0	12	65	P4	1500	Triode Sect.
6CN7	6.3	EV-7806-0	11	56	P4	1200	Triode Sect.
6CN7	6.3	EV-0203-0	0	77	P1★	Diode No. 1
6CN7	6.3	EV-0103-0	0	77	P1★	Diode No. 2
6CQ8	6.3	EV-2637-0	11	80	P4	2800	Tetrode Sect.
6CQ8	6.3	EV-9108-0	16	88	P4	4800	Triode Sect.
6CR6	6.3	JR-7563-2	12	72	P4	1950	Pent. Sect.
6CR6	6.3	JR-0203-0	0	45	P1★	Diode Sect.
6CS6	6.3	JR-3562-7	0	0	500	GRID NO. 1, HOLD DOWN P1 AND PRESS P4
6CS6	6.3	JR-7562-3	0	31	750	GRID NO. 2, HOLD DOWN P1 AND PRESS P4
6CS7	6.3	EV-7608-0	22	75	P4	2200	Triode No. 1
6CS7	6.3	EV-3109-0	27	87	P4	4500	Triode No. 2
6CU5	6.3	JR-2763-0	0	91	7000	HOLD DOWN P1 AND PRESS P4
6CU6	6.3	JR-5047-0	44	89	P4	5500	Cap=P
6CU8	6.3	EV-7236-1	7	86	P4	4000	Pent. Sect.
6CU8	6.3	EV-8901-0	24	83	P4	3300	Triode Sect.
6CX8	6.3	EV-7986-0	11	87	P4	4700	Pent. Sect.
6CX8	6.3	EV-2301-0	15	84	P4	3600	Triode Sect.
6CY5	6.3	JR-3562-0	12	85	3500	HOLD DOWN P1 AND PRESS P4
6CY7	6.3	EV-7608-0	15	48	P4	1000	Triode No. 1
6CY7	6.3	EV-2109-0	65	85	P4	4000	Triode No. 2
6CZ5	6.3	EV-3917-0	10	87	P4	4500

6ST7	6.3	JX-1603-2	20	72	P4	1900	Triode Sect.
6ST7	6.3	JX-0503-6	0	0	P1★	Diode No. 1
6ST7	6.3	JX-0403-6	0	0	P1★	Diode No. 2
6SU7	6.3	JX-4506-1	8	56	P4	1200	Triode No. 1
6SU7	6.3	JX-2103-5	8	56	P4	1200	Triode No. 2
6SV7	6.3	JX-1643-0	6	74	P4	2100	Pent. Sect.
6SV7	6.3	JX-1543-0	0	73	P1★	Diode Sect.
6SZ7	6.3	JX-1603-2	11	56	P4	1200	Triode Sect.
6SZ7	6.3	JX-0503-2	0	15	P1★	Diode No. 1
6SZ7	6.3	JX-0403-2	0	15	P1★	Diode No. 2
6T4	6.3	JR-2305-0	36	88	P4	5000
6T5	6.3	JR-5403-0	P4	Eye Open
6T8	6.3	JR-5423-0	16	48	P4	1000	Eye Closed
6T7	6.3	JR-0307-0	0	30	P1★	Triode Sect. Cap-G
6T7	6.3	JR-0507-0	0	30	P1★	Diode No. 1
6T7	6.3	JR-0407-0	0	30	P1★	Diode No. 2
6T8	6.3	EV-8907-6	11	56	P4	1200	Triode Sect.
6T8	6.3	EV-0607-1	0	77	P1★	Diode No. 1
6T8	6.3	EV-0203-7	0	77	P1★	Diode No. 2
6T8	6.3	EV-0107-8	0	77	P1★	Diode No. 3
6U3	6.3	EV-0903-0	0	60	P3★
6U4	6.3	JX-0503-0	0	65	P3★
6U5	6.3	JR-5403-0	P4	Eye Open
6U5	6.3	JR-5423-0	P4	Eye Closed
6U6	6.3	JR-5347-0	31	86	P4	4200
6U7	6.3	JR-0347-5	15	67	P4	1600	Cap=G
6U8	6.3	EV-2637-0	7	80	P4	2800	Pent. Sect.
6U8	6.3	EV-9108-0	12	90	P4	6200	Triode Sect.
6V3	6.3	EV-0002-0	0	62	P3★	Cap=P Reverse Meter
6V4	6.3	EV-0703-1	0	21	P3★	Plate No. 1
6V4	6.3	EV-0103-7	0	21	P3★	Plate No. 2
6V5	6.3	JX-5340-0	40	86	P4	4100
6V6	6.3	JR-5347-2	13	86	P4	4100
6V7	6.3	JR-0307-0	42	47	P4	975	Triode Sect. Cap-G
6V7	6.3	JR-0507-0	0	35	P1★	Diode No. 1
6V7	6.3	JR-0407-0	0	35	P1★	Diode No. 2
6V8	6.3	EV-6103-8	13	56	P4	1200	Triode Sect.
6V8	6.3	EV-0903-2	0	40	P1★	Diode No. 1
6V8	6.3	EV-0708-0	0	80	P1★	Diode No. 2
6V8	6.3	EV-0203-8	0	80	P1★	Diode No. 3
6W4	6.3	JX-0503-0	0	60	P3★
6W5	6.3	JR-0507-0	0	33	P3★	Plate No. 1
6W5	6.3	JR-0307-0	0	33	P3★	Plate No. 2
6W6	6.3	JR-5347-0	35	87	P4	4500
6W7	6.3	JR-0347-5	20	57	P4	1225	Cap=G
6X4	6.3	JR-0607-3	0	20	P3★	Plate No. 1
6X4	6.3	JR-0307-6	0	20	P3★	Plate No. 2
6X5	6.3	JR-0507-2	0	33	P3★	Plate No. 1
6X5	6.3	JR-0307-2	0	33	P3★	Plate No. 2
6X8	6.3	EV-7986-1	12	81	P4	3000	Pent. Sect.
6X8	6.3	EV-2386-1	20	84	P4	3500	Triode Sect.
6Y5	6.3	JR-0504-0	0	65	P3★	Plate No. 1
6Y5	6.3	JR-0304-0	0	65	P3★	Plate No. 2
6Y6	6.3	JR-5347-0	28	88	P4	5000
6Y7	6.3	JR-5607-3	10	48	P4	1000	Triode No. 1
6Y7	6.3	JR-4307-6	10	48	P4	1000	Triode No. 2
6							

7R7

12Z3

7R7	6.3	JR-6257-0	0	78	P4	2500	Pent. Sect.	12Z3	12.6	JR-0203-0	0	50	P3★
7R7	6.3	JR-0407-2	0	0	P1★	Diode No. 1	14A4	12.6	JR-6207-0	23	79	P4	2600
7R7	6.3	JR-0307-2	0	0	P1★	Diode No. 2	14A5	12.6	JR-6237-0	12	81	P4	3000
7S7	6.3	JR-6257-4	15	65	P4	1500	Heptode Sect.	14A7	12.6	JR-6237-4	0	73	P4	2000
7S7	6.3	JR-4357-6	0	60	P4	1300	Triode Sect.	14AF7	12.6	JR-5607-0	23	79	P4	2600
7T7	6.3	JR-6237-4	0	78	P4	2500	14AF7	12.6	JR-4302-0	23	79	P4	2600
7V7	6.3	JR-6237-4	0	80	P4	2750	14B6	12.6	JR-3207-0	0	53	P4	1100
7W7	6.3	JR-6237-5	0	80	P4	2750	14B6	12.6	JR-0607-2	0	36	P1★
7X6	6.3	JR-0607-0	0	55	P3★	Plate No. 1	14B6	12.6	JR-0507-2	0	36	P1★
7X6	6.3	JR-0302-0	0	55	P3★	Plate No. 2	14B8	12.6	JR-6257-4	16	48	P4	1000
7X7	6.3	JR-3204-0	6	42	P4	900	Triode Sect.	14B8	12.6	JR-4357-6	12	0	P4	500
7X7	6.3	JR-0504-0	0	77	P1★	Diode No. 1	14C5	12.6	JR-6237-0	20	81	P4	3000
7X7	6.3	JR-0607-0	0	77	P1★	Diode No. 2	14C7	12.6	JR-6237-4	22	60	P4	1300
7Y4	6.3	JR-0607-0	0	33	P3★	Plate No. 1	14E6	12.6	JR-3207-0	23	72	P4	1900
7Y4	6.3	JR-0307-0	0	33	P3★	Plate No. 2	14E6	12.6	JR-0607-2	0	30	P1★
7Z4	6.3	JR-0607-0	0	24	P3★	Plate No. 1	14E6	12.6	JR-0507-2	0	30	P1★
7Z4	6.3	JR-0307-0	0	24	P3★	Plate No. 2	14E7	12.6	JR-6257-0	22	60	P4	1300
8AU8	7.5	EV-7986-0	9	87	P4	4500	Pent. Sect.	14E7	12.6	JR-0407-2	0	0	P1★
8AU8	7.5	EV-2301-0	15	86	P4	4000	Triode Sect.	14E7	12.6	JR-0307-2	0	0	P1★
8AW8A	7.5	EV-7986-3	10	90	P4	6000	Pent. Sect.	14F7	12.6	JR-5607-3	10	60	P4	1300
8AW8A	7.5	EV-2301-9	15	78	P4	2500	Triode Sect.	14F7	12.6	JR-4302-6	10	60	P4	1300
8BABA	7.5	EV-7986-0	11	88	P4	5000	Pent. Sect.	14F8	12.6	HS-8605-0	7	85	P4	4000
8BABA	7.5	EV-2301-0	30	79	P4	2700	Triode Sect.	14F8	12.6	HS-1304-0	7	85	P4	4000
8BH8	7.5	EV-7986-0	7	88	P4	5000	Pent. Sect.	14H7	12.6	JR-6237-4	0	81	P4	3000
8BH8	7.5	EV-2301-0	27	83	P4	3300	Triode Sect.	14J7	12.6	JR-6257-4	21	35	P4	800
8BN8	7.5	EV-8709-0	20	73	P4	2000	Triode Sect.	14J7	12.6	JR-4357-6	6	48	P4	1000
8BN8	7.5	EV-0603-0	0	78	P1★	Diode No. 1	14N7	12.6	JR-5607-3	23	73	P4	2000
8BN8	7.5	EV-0102-0	0	78	P1★	Diode No. 2	14N7	12.6	JR-4302-6	23	73	P4	2000
8CG7	7.5	EV-7608-9	23	79	P4	2600	Triode No. 1	14Q7	12.6	JR-6237-4	0	35	P4	800
8CG7	7.5	EV-2103-9	23	79	P4	2600	Triode No. 2	14Q7	12.6	JR-4237-6	0	35	P4	800
8CM7	7.5	EV-7603-0	27	73	P4	2000	Triode No. 1	14R7	12.6	JR-6257-0	0	78	P4	2500
8CM7	7.5	EV-8109-0	24	87	P4	4400	Triode No. 2	14R7	12.6	JR-0407-2	0	0	P1★
8CN7	7.5	EV-7806-0	11	56	P4	1200	Triode Sect.	14R7	12.6	JR-0307-2	0	0	P1★
8CN7	7.5	EV-0203-0	0	77	P1★	Diode No. 1	14S7	12.6	JR-6257-4	15	65	P4	1500
8CN7	7.5	EV-0103-0	0	77	P1★	Diode No. 2	14S7	12.6	JR-4357-6	0	60	P4	1300
8CS7	7.5	EV-7608-0	22	75	P4	2200	Triode No. 1	14V7	12.6	JR-6237-4	0	80	P4	2750
8CS7	7.5	EV-3109-0	27	87	P4	4500	Triode No. 2	14W7	12.6	JR-6237-5	0	80	P4	2750
8CY7	7.5	EV-7608-0	15	48	P4	1000	Triode No. 1	14X7	12.6	JR-0504-0	0	77	P1★
8CY7	7.5	EV-2109-0	65	85	P4	4000	Triode No. 2	14X7	12.6	JR-0607-0	0	77	P1★
8SN7	7.5	JX-4506-0	23	79	P4	2600	Triode No. 1	14Y4	12.6	JR-0607-0	0	33	P3★
8SN7	7.5	JX-2103-0	23	79	P4	2600	Triode No. 2	14Y4	12.6	JR-0307-0	0	33	P3★
9AU7	10.0	EV-7608-0	24	75	P4	2200	Triode No. 1	14Z3	12.6	JR-0203-0	0	43	P3★
9AU7	10.0	EV-2103-0	24	75	P4	2200	Triode No. 2	15	2.0	JR-0234-0	0	27	700
9CL8	10.0	EV-9678-0	10	84	P4	3500	Tetrode Sect.	15A6	12.6	EV-2713-6	8	91	P4	7500
9CL8	10.0	EV-1203-0	12	89	P4	6000	Triode Sect.	17AV5	20.0	JR-2573-0	22	89	P4	5500
9U8	10.0	EV-2637-0	7	80	P4	2800	Pent. Sect.	17AX4	20.0	JX-0503-0	0	35	P3★
9U8	10.0	EV-9108-0	12	90	P4	6200	Triode Sect.	17C5	20.0	JR-2763-0	20	90	6000
9X8	10.0	EV-7986-1	12	81	P4	3000	Pent. Sect.	17CA5	20.0	JR-2763-0	12	88	P4	5000
9X8	10.0	EV-2386-1	20	84	P4	3500	Triode Sect.	17DQ6	20.0	JR-5047-0	25	90	6000
10	7.5	JR-3200-0	42	58	P4	1250	17H3	20.0	EV-0301-0	0	45	P3★
10C8	10.0	EV-8679-0	13	85	P4	4000	Pent. Sect.	17L6	20.0	JR-5347-0	11	88	5500
10C8	10.0	EV-2103-0	15	84	P4	3500	Triode Sect.	17R5	20.0	JR-2763-0	20	88	5000
10DA7	10.0	EV-7608-0	22	79	P4	2600	Triode No. 1	18A5	20.0	JR-2573-0	40	88	P4	4800
10DA7	10.0	EV-3109-0	55	89	P4	5400	Triode No. 2	19	2.0	JR-4500-0	23	48	P4	1000
10DE7	10.0	EV-7608-0	29	73	P4	2000	Triode No. 1	19	2.0	JR-3200-0	23	48	P4	1000
10DE7	10.0	EV-2109-0	55	89	P4	6500	Triode No. 2	19AU4	20.0	JX-0503-0	0	60	P3★
11C5	10.0	JR-2763-0	23	87	P4	4500	19BG6	20.0	JR-5073-0	12	90	P4	6000
12A	5.0	JR-3200-0	44	68	P4	1650	19C8	20.0	EV-8907-0	8	58	P4	1250
12A4	12.6	EV-2901-0	25	91	P4	7800	19C8	20.0	EV-8607-0	0	77	P1★
12A5	12.6	JR-4235-0	35	70	P4	1800	19C8	20.0	EV-8203-0	0	77	P1★
12A6	12.6	JR-5347-2	18	81	P4	3000	19C8	20.0	EV-8107-0	0	77	P1★
12A7	12.6	JR-0236-5	40	47	P4	975	Pent. Sect. Cap-G	19J6	20.0	JR-5207-6	22	78	P4	2500
12A7	12.6	JR-0504-2	0	40	P3★	Rect. Sect.	19J6	20.0	JR-6307-5	22	78	P4	2500
12A8	12.6	JR-0347-5	11	48	P4	1000	Pent. Sect. Cap-G	19T8	20.0	EV-8907-6	8	56	P4	1200
12A8	12.6	JR-5647-3	11	73	P4	300	Disc. Sect. OK ABOVE 150	19T8	20.0	EV-0607-1	0	77	P1★
12AB5	12.6	EV-3917-0	13	86	P4	4100	19T8	20.0	EV-0203-7	0	77	P1★
12AC6	12.6	JR-2657-3	20	15	P1★	OK ABOVE DIODES OK. MAKE NO GAS TEST	19T8	20.0	EV-0107-8	0	77	P1★
12AD6	12.6	JR-7652-3	30	25	P1★	Make no gas test	19V8	20.0	EV-6103-8	13	56	P4	1200
12AD7	12.6	EV-7608-0	12	58	P4	1250	Triode No. 1	19V8	20.0	EV-0903-2	0	40	P1★
12AD7	12.6	EV-2103-0	12	58	P4	1250	Triode No. 2	19V8	20.0	EV-0708-6	0	80	P1★
12AE6	12.6	JR-0702-3	0	0	P1★	TRIODE SECT. OK ABOVE 300 OHM 300 SCALE. MAKE NO GAS TEST	19V8	20.0	EV-0203-8	0	80	P1★
12AE6	12.6	JR-0602-0	0	26	P1★	Diode No. 1	19X3	20.0	EV-0903-0	0	60	P3★
12AE6	12.6	JR-0502-0	0	26	P1★	Diode No. 2	19X8	20.0	EV-7986-1	12	81	P4	3000
12AE7	12.6	EV-0608-7	0	67	P1★	TRIODE NO. 1	19X8	20.0	EV-2386-1	20	84	P4	3500
12AE7	12.6	EV-0103-2	0	70	P1★	MAKE NO GAS TEST	19Y3	20.0	EV-0903-0	0	60	P3★
12AF6	12.6	JR-3567-2	26	55	1150	HOLD DOWN PI AND PRESS PA	19X3	20.0	EV-0903-0	0	60	P3★
12AG6	12.6	JR-7652-3	30	50	P1★	Make no gas test	22	3.0	JR-0230-0	23	0	500
12AH7	12.6	JX-6604-3	22	73	P4	2000	Triode No. 1	24A	2.5	JR-0234-0	12	48	P4	1000
12AH7	12.6	JX-2301-6	22	73	P4	2000	Triode No. 2	25A6	25.0	JR-3200-0	30	73	P4	2000
12AJ6	12.6	JR-0702-3	0	0	P1★	TRIODE SECT. OK ABOVE 300 OHM 300 SCALE. MAKE NO GAS TEST	25A6	25.0	JR-5347-0	25	76	P4	2300
12AJ6	12.6	JR-0602-0	0	26	P1★	Diode No. 1	25A7	25.0	JR-5347-6	28	70	P4	1800
12AJ6	12.6	JR-0502-0	0	26	P1★	Diode No. 2	25A7	25.0	JR-0602-3	0	50	P3★
12AL5	12.6	JR-0703-0	0	78	P1★	Diode No. 1	25AC5	25.0	JR-5307-0	0	65	P4	1600
12AL5	12.6	JR-0205-0	0	78	P1★	Diode No. 2	25AV5	25.0	JR-2573-0	50	85	P4	3900
12AL8	12.6	EV-0367-2	0	78	P1★	TRIODE SECT. MAKE NO GAS TEST	25AX4	25.0	JX-0503-0	0	35	P3★
12AL8	12.6	EV-0109-8	0	0	P1★	TRIODE SECT. OK ABOVE 300 OHM 300 SCALE. MAKE NO GAS TEST	25B5	25.0	JR-4235-0	0	73	P4	2000
12AQ5	12.6	JR-3562-0	10	86	P4	4100	25B6	25.0	JR-5347-0	55	85	P4	4000
12AT6	12.6	JR-3702-0	10	60	P4	1300	Triode Sect.	25B8	25.0	JR-0342-0	15	70	P4	1800
12AT6	12.6	JR-3602-0	0	26	P1★	Diode No. 1	25B8	25.0	JR-7506-0	0	65	P4	1500
12AT6	12.6	JR-3502-0	0	26	P1★	Diode No. 2	25BK5	25.0	EV-3186-0	0	88	P4	5000
12AT7	12.6	EV-7608-0	10	85	P4	4000	Triode No. 1	25BQ6	25.0	JR-5047-0	42	87	P4	4500
12AT7	12.6	EV-2103-0	10	85	P4	4000	Triode No. 2	25C5	25.0	JR-2763-0	20	91	7500
12AU6	12.6	JR-3567-2	11	76	P4	2300	25C6	25.0	JR-5347-0	28	88	P4	5000
12AU7	12.6	EV-7608-0	24	75	P									

12BE6

26A6

12BE6	12.6	JR-7562-3	0	35	800	Appl Sect. Hold down P1 and Press P4 for reading	26A6	25.0	JR-3567-2	0	81	P4	3000	Appl Sect. Hold down P1 and Press P4 for reading
12BE6	12.6	JR-3602-7	20	90	6500	Osc. Sect.	26A7	25.0	JW-2751-3	0	87	4500	Triode Sect.
12BF6	12.6	JR-3702-0	19	72	1900	Triode Sect.	26A7	25.0	JW-3451-2	0	87	4500	Triode Sect.
12BF6	12.6	JR-3602-0	0	26	Diode No. 1	26BK6	25.0	JR-3702-5	0	58	P1★	1250	Diode No. 1
12BF6	12.6	JR-3502-0	0	26	Diode No. 2	26BK6	25.0	JR-0602-5	0	57	P1★	Diode No. 2
12BH7	12.6	EV-7608-2	32	77	2380	Triode No. 1	26BK6	25.0	JR-0502-7	0	57	P1★	Triode Sect.
12BH7	12.6	EV-2103-7	32	77	2380	Triode No. 2	26C6	25.0	JR-3702-0	23	72	P4	1900	Diode No. 1
12BK5	12.6	EV-3186-0	0	88	5000	26C6	25.0	JR-3602-0	0	30	P1★	Diode No. 2
12BK6	12.6	JR-3702-5	0	58	1250	Triode Sect.	26C6	25.0	JR-3502-0	0	30	P1★
12BK6	12.6	JR-0602-5	0	57	Diode No. 1	26D6	25.0	JR-7562-3	0	35	800	Osc. Sect.
12BK6	12.6	JR-0502-7	0	57	Diode No. 2	26D6	25.0	JR-3602-7	20	90	P4	6500	Osc. Sect.
12BL6	12.6	JR-2657-3	22	25	Make no gas test	26E6	25.0	JR-5347-0	25	90	P4	6000
12BN6	12.6	JR-2753-6	6	27	700	LIMIT END HOLD DOWN P1 AND PRESS P4	26Z6W	25.0	EV-0608-0	0	50	P3★	Plate No. 1
12BN6	12.6	JR-6753-2	13	0	500	HOLD DOWN P1 AND PRESS P4	26Z6W	25.0	EV-0103-0	0	50	P3★	Plate No. 2
12BQ6	12.6	JR-5047-0	42	87	4500	27	2.5	JR-3204-0	41	48	P4	1000
12BR7	12.6	EV-2103-0	10	85	4000	Triode Sect.	28D7	25.0	JR-7536-2	13	83	3400
12BR7	12.6	EV-0708-0	0	78	Diode No. 1	28D7	25.0	JR-2436-7	13	83	900
12BR7	12.6	EV-0608-0	0	78	Diode No. 2	30	2.0	JR-3200-0	43	42	P4	925
12BT6	12.6	JR-3702-0	12	60	1300	Triode Sect.	31	2.0	JR-3200-0	41	44	P4	925
12BT6	12.6	JR-3602-0	0	57	Diode No. 1	32	2.0	JR-0230-0	20	20	P4	640	Cap-G HOLD DOWN P1 AND PRESS P4 FOR READING
12BT6	12.6	JR-3502-0	0	57	Diode No. 2	32L7	35.0	JR-5347-0	32	88	P4	4800	Ampl. Sect.
12BU6	12.6	JR-3702-0	28	65	1500	Triode Sect.	32L7	35.0	JR-0602-3	0	60	P3★	Rect. Sect.
12BU6	12.6	JR-3602-0	0	50	Diode No. 1	33	2.0	JR-3240-0	27	60	P4	1300
12BU6	12.6	JR-3502-0	0	50	Diode No. 2	33	2.0	JR-3240-0	27	60	P4	1300	Triode No. 1
12BV7	12.6	EV-2781-3	0	90	6500	34	2.0	JR-0230-0	16	15	600	Triode No. 2, Cap-G
12BW4	12.6	EV-0709-1	0	20	Plate No. 1	35	2.5	JR-0234-0	22	49	P4	1020	Cap-G
12BW4	12.6	EV-0109-7	0	20	Plate No. 2	35A5	35.0	JR-6237-0	20	90	P4	5900
12BY7	12.6	EV-2781-3	0	90	6500	Triode No. 1	35B5	35.0	JR-3562-0	23	87	P4	4500
12BZ7	12.6	EV-7608-0	14	76	2300	Triode No. 2	35C5	35.0	JR-2763-0	23	87	P4	4500
12BZ7	12.6	EV-2103-0	14	76	2300	Triode No. 2	35CD6	35.0	JR-0703-0	35	90	P4	6500	Cap=P
12C5	12.6	JR-2763-0	20	91	7500	35CL7	35.0	JR-5347-0	21	87	P4	4600
12C8	12.6	JR-0367-3	20	55	1150	Pent. Sect. Cap-G	35W4	BLST	JR-0367-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12C8	12.6	JR-0507-3	0	18	Diode No. 1	35W4	BLST	JR-0247-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12C8	12.6	JR-0407-3	0	18	Diode No. 2	35Y4	35.0	JR-0207-0	0	65	P3★	Rect. Sect.
12CA5	12.6	JR-2763-0	20	89	5500	35Z3	35.0	JR-0207-0	0	65	P3★
12CM6	12.6	EV-3917-0	13	86	4100	35Z4	35.0	JR-0507-0	0	67	P3★
12CM6	12.6	EV-0673-2	0	55	Make no gas test	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CN5	12.6	JR-7563-2	14	74	2200	Pent. Sect.	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CR6	12.6	JR-7563-2	14	74	2200	Diode Sect.	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CR6	12.6	JR-0203-0	0	45	HOLD DOWN P1 AND PRESS P4	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CS6	12.6	JR-3562-7	0	0	500	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CS6	12.6	JR-7562-3	0	31	750	HOLD DOWN P1 AND PRESS P4	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CT8	12.6	EV-8679-0	9	87	4500	Pent. Sect.	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CT8	12.6	EV-2103-0	15	86	4000	Triode Sect.	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CU5	12.6	JR-2763-0	0	91	7000	HOLD DOWN P1 AND PRESS P4	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12CU6	12.6	JR-5047-0	44	89	5500	Cap-P	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12D4	12.6	JX-0503-0	0	50	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12DB5	12.6	EV-3912-0	0	92	8000	HOLD DOWN P1 AND PRESS P4	35Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12DF5	12.6	EV-0608-0	0	20	Plate No. 1	35Z6	35.0	JR-0507-0	0	67	P3★	Plate No. 1
12DF5	12.6	EV-0103-0	0	20	Plate No. 2	35Z6	35.0	JR-0304-0	0	67	P3★	Plate No. 2
12DM5	12.6	JR-2763-0	20	91	7500	HOLD DOWN P1 AND PRESS P4	35Z6	35.0	JR-0304-0	0	67	P3★	Plate No. 2
12DQ6	12.6	JR-5047-0	25	90	6000	Cap-G	36	6.3	JR-0234-0	31	50	P4	1050	Cap-G
12DF6	12.6	JR-0407-0	12	48	1000	Cap-G	37	6.3	JR-3204-0	39	42	P4	900
12F8	12.6	EV-9237-8	25	0	38	6.3	JR-0234-0	35	50	P4	1050	Cap-G
12F8	12.6	EV-0607-0	0	30	38	6.3	JR-0234-0	35	50	P4	1000	Cap-G
12F8	12.6	EV-0107-0	0	30	39/44	5.0	JR-3200-0	32	P4	200	OK above 125
12G4	12.6	JR-6307-0	23	79	2600	40Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12G8	12.6	EV-0607-8	0	65	40Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12G8	12.6	EV-0102-3	0	25	41	6.3	JR-4235-0	34	67	P4	1600
12G8	12.6	EV-0507-2	0	73	42	6.3	JR-4235-0	23	73	P4	2000
12H6	12.6	JR-0304-2	0	73	43	25.0	JR-4235-0	22	76	P4	2300
12H6	12.6	JR-0304-2	0	73	45	2.5	JR-3200-0	57	71	P4	1850
12J5	12.6	JR-5307-2	23	79	2600	45Z3	50.0	HT-0208-0	0	58	P3★
12J7	12.6	JR-0347-5	19	57	1225	45Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12J8	12.6	EV-0362-1	0	65	45Z5	BLST	JR-0537-0	Short on 1-2-3-4-5 above 135-, 136-, or 138-10000
12J8	12.6	EV-0907-0	0	78	46	2.5	JR-3240-0	0	73	P4	2000
12J8	12.6	EV-0807-0	0	82	47	2.5	JR-3240-0	0	73	P4	2000
12K5	12.6	JR-2753-0	10	80	3000	HOLD DOWN P1 AND PRESS P4	48	25.0	JR-4235-0	45	73	P4	2000
12K7	12.6	JR-0347-5	18	63	1450	Cap-G	49	2.0	JR-3240-0	49	64	P4	1125
12K8	12.6	JR-5347-6	0	42	900	Hapt. Sect. Cap-G	50	7.5	JR-3200-0	60	65	P4	1500
12K8	12.6	JR-5647-3	8	56	1200	Triode Sect.	50A5	50.0	JR-6237-0	10	91	P4	7500
12L6	12.6	JR-5347-0	0	92	8000	HOLD DOWN P1 AND PRESS P4	50B5	50.0	JR-3562-0	20	91	7500	HOLD DOWN P1 AND PRESS P4
12L8	12.6	JW-2751-3	0	69	1700	Pent. No. 2	50BK5	50.0	EV-3186-0	0	88	P4	5000
12L8	12.6	JW-3451-2	0	69	1700	Triode Sect. Cap-G	50C5	50.0	JR-2763-0	20	91	7500	HOLD DOWN P1 AND PRESS P4
12O7	12.6	JR-0307-2	18	35	800	50C6	50.0	JR-5347-2	28	88	P4	5000
12O7	12.6	JR-0507-3	0	27	50L6	50.0	JR-5347-0	0	92	8000	HOLD DOWN P1 AND PRESS P4 FOR READING
12O7	12.6	JR-0407-3	0	27	50X6	50.0	JR-0607-5	0	60	P3★	Plate No. 1
12R5	12.6	JR-2763-0	20	91	7000	HOLD DOWN P1 AND PRESS P4	50X6	50.0	JR-0302-5	0	60	P3★	Plate No. 2
12S8	12.6	JX-0601-0	9	42	900	Triode Sect. Cap-G	50Y6	50.0	JR-0507-0	0	62	P3★	Plate No. 1
12S8														

75

75	6.3	JR-0205-0	14	31	P4	750	Triode Sect. Cap-G	5636	6.3DW-1572-4	20	57	P4	1600	Grid No. 1
75	6.3	JR-0405-2	0	25	P1★	Diode No. 1	5636	6.3DW-4572-1	22	0	500	GRID NO. 3 HOLD DOWN P1 AND PRESS P4
75	6.3	JR-0305-2	0	25	P1★	Diode No. 2	5637	6.3 DU-2105-0	22	65	P4	1500	
75MG	6.3	JR-0407-0	14	31	P4	760	Triode Sect. Cap-G	5638	6.3 EW-3152-0	22	73	P4	2000	
75MG	6.3	JR-0507-0	0	25	P1★	Diode No. 1	5639	6.3DW-1572-0	15	87	P4	4700	
75MG	6.3	JR-0607-0	0	25	P1★	Diode No. 2	5640	6.3DW-1572-0	44	87	P4	4500	
76	6.3	JR-3204-0	30	63	P4	1450	Cap-G	5641	6.3DW-0205-0	0	40	P3★	
77	6.3	JR-0235-4	20	57	P4	1225	Cap-G	5642	1.1 BS-0000-0	0	0	P3★	TOP LEAD - P. CONNECT FIL LEADS TO PINS 1 AND 2. OK ABOVE 500 OH 3000 SCALE
78	6.3	JR-0235-4	24	63	P4	1450	Cap-G	5643	6.3DW-7105-2	#	65	P3★	STRIKES AT ABOUT 75
79	6.3	JR-0504-0	10	48	P4	1000	Triode No. 1, Cap-G	5645	6.3 FT-4102-0	29	75	P4	2200	
80	5.0	JR-0300-0	0	20	P3★	Plate No. 1	5646	6.3 FT-4102-0	19	62	P4	1400	
80	5.0	JR-0200-0	0	15	P3★	Plate No. 2	5647	6.3 CT-0104-0	0	79	P1★	Diode
81	7.5	JR-0200-0	0	60	P1★	Plate No. 1	5654	6.3 JR-3562-0	0	83	P4	3250	
82	2.5	JR-0300-0	0	54	P3★	Plate No. 1	5659	12.6 JR-5347-0	18	81	P4	3000	
82	2.5	JR-0200-0	0	54	P3★	Plate No. 2	5660	12.6 JR-0367-0	20	55	P4	1150	PENT. SECT. CAP-G
83	5.0	JR-0300-0	0	62	P3★	Plate No. 1	5660	12.6 JR-0567-0	0	40	P1★	Diode No. 1
83	5.0	JR-0200-0	0	62	P3★	Plate No. 2	5660	12.6 JR-0467-0	0	40	P1★	Diode No. 2
83V	5.0	JR-0300-0	0	60	P3★	Plate No. 1	5661	12.6 JR-4765-3	12	73	P4	2000	
83V	5.0	JR-0200-0	0	60	P3★	Plate No. 2	5662	6.3 JR-3705-0	#	95	P5★	Strikes at about 24
84	6.3	JR-0304-0	0	45	P3★	Plate No. 1	5663	6.3 JR-3752-0	#	70	P3★	Strikes at about 70
84	6.3	JR-0204-0	0	45	P3★	Plate No. 2	5670	6.3 KR-7608-0	17	88	P4	5000	Triode No. 1
85	6.3	JR-0205-0	42	47	P4	975	Triode Sect. Cap-G	5672	6.3 KR-3402-0	17	88	P4	5000	Triode No. 2
85	6.3	JR-0405-2	0	25	P1★	Diode No. 1	5672	1.1 DV-4120-0	32	21	P4	650	HOLD DOWN P1 AND PRESS P4
85	6.3	JR-0305-2	0	25	P1★	Diode No. 2	5676	1.1 ES-3100-0	30	67	P4	1600	
85AS	6.3	JR-0205-0	25	53	P4	1100	Triode Sect. Cap-G	5677	1.1 ES-3100-0	38	21	P4	650	
85AS	6.3	JR-0405-2	0	25	P1★	Diode No. 1	5678	1.1 DV-4120-0	12	31	P4	750	HOLD DOWN P1 AND PRESS P4
85AS	6.3	JR-0305-2	0	25	P1★	Diode No. 2	5679	6.3 JR-0607-5	0	70	P1★	Diode No. 1
89/89Y	6.3	JR-0235-4	29	66	P4	1550	Cap-G	5679	6.3 JR-0302-5	0	70	P1★	Diode No. 2
99	3.0	JR-3200-0	57	73	P4	425	OK Above 270	5686	6.3 EV-2763-0	0	81	P4	3000	
112A	5.0	JR-3200-0	45	68	P4	1650	5687	12.6 EV-7906-1	26	91	P4	7500	Triode No. 1
CK113	50.0	JR-5347-6	48	70	P4	1800	Pent. Sect.	5687	12.6 EV-2103-9	26	91	P4	7500	Triode No. 2
CK113	50.0	JR-0602-0	0	60	P3★	Rect. Sect.	5690	6.3 JW-0507-3	0	60	P3★	Unit No. 1
HY114	1.5	JR-0000-0	27	63	P4	1100	Left Cap=G	5690	6.3 BS-0304-5	0	60	P3★	Unit No. 2
117L/M7	117.0	JR-4357-0	22	85	P4	4000	Pent. Sect.	5691	6.3 JX-4506-1	7	58	P4	1250	Triode No. 1
117L/M7	117.0	JR-0602-0	0	65	P3★	Rect. Sect.	5691	6.3 JX-2103-5	7	58	P4	1250	Triode No. 2
117N7	117.0	JR-4356-0	37	88	P4	5000	Pent. Sect.	5692	6.3 JX-4506-1	23	79	P4	2600	Triode No. 1
117N7	117.0	JR-0700-0	0	70	P3★	Rect. Sect.	5692	6.3 JX-2103-5	23	79	P4	2600	Triode No. 2
117P7	117.0	JR-4356-0	20	85	P4	4000	Reverse Meter	5693	6.3 JR-4765-3	11	58	P4	1650	
117P7	117.0	JR-0700-0	0	70	P3★	Rect. Sect.	5694	6.3 JR-4302-0	0	73	P4	2000	Triode No. 1
117Z3	117.0	JR-0506-0	0	60	P3★	Pent. Sect.	5694	6.3 JR-5607-0	0	73	P4	2000	Triode No. 2
117Z4	117.0	JR-0507-0	0	65	P3★	Reverse Meter	5696	6.3 JR-3602-5	#	95	P5★	Strikes at about 27
117Z6	117.0	JR-0507-0	0	65	P3★	5702	6.3 DU-7126-5	24	65	P4	1500	
117Z6	117.0	JR-0304-0	0	65	P3★	Plate No. 1	5703	6.3 DU-5106-0	26	81	P4	3000	
X-155	6.3	EV-7608-9	20	88	P4	5000	Triode No. 1	5704	6.3 CT-0104-0	0	79	P1★	Diode
X-155	6.3	EV-2103-9	20	88	P4	5000	Triode No. 2	5718	6.3DW-1805-7	23	89	P4	5500	
TS251	50.0	JR-5347-6	28	70	P4	1800	Pent. Sect.	5719	6.3DW-1805-7	17	65	P4	1500	
TS251	50.0	JR-0602-3	0	50	P3★	Rect. Sect.	5725	6.3 JR-3562-7	0	73	P4	2000	
396A	6.3	KR-7608-0	20	88	P4	5000	Triode No. 1	5726	6.3 JR-0703-0	0	78	P1★	Diode No. 1
396A	6.3	KR-3402-0	20	88	P4	5000	Triode No. 2	5726	6.3 JR-0205-0	0	78	P1★	Diode No. 2
399A	1.1	DX-6210-0	0	48	1000	HOLD DOWN P1 AND PRESS P4	5727	6.3 JR-3602-5	#	95	P5★	Strikes at about 27
401A	6.3	JR-3567-0	10	73	2000	HOLD DOWN P1 AND PRESS P4	5731	6.3 JR-4306-0	20	75	P4	2200	
403A	6.3	JR-3562-0	24	65	P4	1500	HOLD DOWN P1 AND PRESS P4	5732	6.3 JR-0347-5	18	63	P4	1450	Cap-G
403B	6.3	JR-3562-0	0	86	P4	3200	HOLD DOWN P1 AND PRESS P4	5742	4.3 JR-3200-0	10	39	P4	850	
420A	12.6	EV-6807-3	0	56	P4	1200	Triode No. 1	5749	6.3 CT-4105-0	16	73	P4	2000	
420A	12.6	EV-3102-6	0	56	P4	1200	Triode No. 2	5749	6.3 JR-3567-2	0	79	P4	2700	
GL502	6.3	JR-5367-0	#	55	P3★	Strikes at about 70	5750	6.3 JR-7562-3	0	35	800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
CK502AX	1.1	DV-4120-0	21	7	550	HOLD DOWN P1 AND PRESS P4	5750	6.3 JR-3602-7	20	90	P4	6500	Osc. Sect.
CK503AX	1.1	DV-4120-0	23	7	550	HOLD DOWN P1 AND PRESS P4	5751	12.6 EV-7608-0	12	58	P4	1250	Triode No. 1
CK505AX	0.6	DV-4210-0	0	0	P1★	OK ABOVE 275 OH 3000 SCALE	5751	12.6 EV-2103-0	12	58	P4	1250	Triode No. 2
CK506AX	1.1	DV-4120-0	35	0	P5★	HOLD DOWN P1 AND PRESS P4	5755	12.6 EV-6807-3	0	56	P4	1200	Triode No. 1
CK510AX	0.6	EX-1230-0	0	0	P5★	OK ABOVE 100 OH 3000 SCALE	5755	12.6 EV-3102-6	0	56	P4	1200	Triode No. 2
CK510AX	0.6	EX-6530-0	0	0	P1★	OK ABOVE 100 OH 3000 SCALE	5763	6.3 EV-9167-3	0	88	P4	5000	
CK512AX	0.6	DV-4210-0	0	0	P1★	OK ABOVE 300 OH 3000 SCALE	5784	6.3 DU-7126-5	12	75	P4	2200	
CK518AX	1.1	DV-4120-0	45	0	P5★	OK ABOVE DIODES OK	5785	1.1 GX-0100-0	0	0	P1★	Diode
CK522AX	1.1	DV-4120-0	40	0	P5★	OK ABOVE DIODES OK	5812	6.3 JR-3560-2	28	86	P4	4300	
CK523AX	1.1	DV-4120-0	47	0	P5★	OK ABOVE DIODES OK	5814	12.6 EV-7608-0	16	80	P4	2775	Triode No. 1
CK524AX	1.1	DV-4120-0	76	0	P5★	OK ABOVE DIODES OK	5814	12.6 EV-2103-0	16	80	P4	2775	Triode No. 2
CK525AX	1.1	DV-4120-0	50	0	P5★	OK ABOVE DIODES OK	5823	BLST AP-8301-0	100	92	P5★
CK526AX	1.1	DV-4120-0	59	0	P5★	OK ABOVE DIODES OK	5824	25.0 JR-5347-0	55	85	P4	4000	
CK527AX	1.1	DV-4120-0	36	0	P5★	OK ABOVE DIODES OK	5825	1.5 JR-0000-0	0	0	P5★	CAP - P. OK ABOVE 500 OH 3000 SCALE
CK528AX	1.1	DV-4120-0	37	0	P5★	OK ABOVE DIODES OK	5829	6.3 DV-0607-0	0	78	P1★	Diode No. 1
CK529AX	1.1	DV-4120-0	64	0	P5★	OK ABOVE DIODES OK	5829	6.3 DV-0102-0	0	78	P1★	Diode No. 2
CK533AX	1.1	DV-4120-0	43	0	P5★	OK ABOVE DIODES OK	5839	25.0 JR-0507-3	0	25	P3★	Plate No. 1
CK541DX	1.1	DV-4120-0	37	0	P5★	OK ABOVE DIODES OK	5839	25.0 JR-0307-5	0	25	P3★	Plate No. 2
CK542DX	1.1	DV-4210-0	15	0	P1★	OK ABOVE 300 OH 3000 SCALE	5840	6.3DW-1574-0	19	78	P4	2500	
CK543DX	0.6	DV-4210-0	0	0	P1★	OK ABOVE 300 OH 3000 SCALE	5844	6.3 JR-5207-0	26	81	P4	3000	Triode No. 1
CK544DX	1.1	DV-4120-0	32	0	P5★	OK ABOVE DIODES OK	5844	6.3 JR-6307-0	26	81	P4	3000	Triode No. 2
GL546	6.3	JR-3752-0	#	66	P3★	OK ABOVE 300 OH 3000 SCALE	5851	2.5 HR-8360-0	33	67	P4	1600	
CK547DX	1.1	DV-4120-0	33	0	P5★	OK ABOVE 500 OH 3000 SCALE	5852	6.3 JR-0507-0	0	0	P3★	Plate No. 1
CK548DX	1.1	DV-4120-0	49	0	P5★	OK ABOVE 275 OH 3000 SCALE	5852	6.3 JR-0307-0	0	0	P3★	Plate No. 2
CK556AX	1.1	ES-3100-0	30	67	P4	1600	OK ABOVE 300 OH 3000 SCALE	5879	6.3 EV-1873-9	20	48			

885

6005

885	2.5	JR-3204-0	# 95	P5★	Strikes at about 68	5005	6.3	JR-3562-0	10	85	P4	4120	
SD917A	6.3	DU-2105-0	22	65	P4	1500	6007	1.1	DV-4210-0	13	0	P1★	ON ABOVE 300 OR 3000 SCALE
SN944	6.3	EW-3051-2	15	77	P4	2400	6008	0.6	DV-4210-0	13	0	P1★	ON ABOVE 300 OR 3000 SCALE
SN946	6.3	CT-0104-0	0	79	P1★	6012	6.3	JR-3502-7	#	94	P5★	STRIKES AT ABOUT 30
SN946B	6.3	CT-0104-0	0	79	P1★	6021	6.3	JDW-7805-0	25	78	P4	2500	Triode No. 1
SN947C	6.3	CU-6135-0	44	87	P4	4500	6021	6.3	JDW-2104-0	25	78	P4	2500	Triode No. 2
SN947D	6.3	JDW-1572-0	44	87	P4	4500	6026	6.3	EV-7803-0	25	86	P4	4300	
SN949C	6.3	JDW-7105-2	# 65	P3★	6029	1.1	CU-3100-0	42	73	P4	2000	
950	2.0	JR-3240-0	45	45	P4	950	6052	6.3	JDW-0507-4	0	52	P3★	Plate No. 1
951	2.0	JR-0230-0	17	35	6052	6.3	JDW-0102-4	0	52	P3★	Plate No. 2
SN953D	6.3	JDW-1572-0	15	87	P4	4700	6055	25.0	ODW-1805-0	36	73	P4	2000	
954	6.3	JR-7036-4	23	53	P4	1100	6072	12.6	EV-7608-0	18	58	P4	1250	Triode No. 1
SN954	6.3	ES-0103-0	0	40	P3★	6072	12.6	EV-2103-0	18	58	P4	1250	Triode No. 2
SN954B	6.3	JDW-0205-0	0	40	P3★	6080	7.5	JX-4506-1	100	83	P4	3400	Triode No. 1
955	6.3	JR-4306-0	24	72	P4	1900	6080	7.5	JX-2103-5	100	83	P4	3400	Triode No. 2
SN955B	6.3	JDW-1708-4	19	81	P4	3000	6082	25.0	JX-4506-1	100	83	P4	3400	Triode No. 1
SN955B	6.3	JDW-2508-4	19	81	P4	3000	6082	25.0	JX-2103-5	100	83	P4	3400	Triode No. 2
956	6.3	JR-7036-4	17	65	P4	1500	6084	6.3	EV-9613-8	18	71	P4	1850	
SN956B	1.1	BS-0000-0	0	0	P3★	6085	12.6	EV-7608-0	18	80	P4	2700	Triode No. 1
957	1.5	JR-4300-0	33	21	P4	650	6085	12.6	EV-2103-0	18	80	P4	2700	Triode No. 2
SN957A	6.3	FT-4102-0	29	75	P4	2200	6086	20.0	EV-2613-9	10	90	P4	6500	
958	1.5	JR-4300-0	39	56	P4	1200	6087	5.0	HR-0600-0	0	22	P3★	Plate No. 1
959	1.5	JR-7030-0	20	15	600	6087	5.0	HR-0400-0	0	22	P3★	Plate No. 2
SN972D	6.3	JDW-1574-0	19	73	P4	2000	6088	1.1	DV-4120-0	20	0	500	HOLD DOWN PI AND PRESS P4
SN973B	6.3	GT-1574-0	19	78	P4	2500	6094	6.3	DV-1428-0	10	86	P4	4100	
SN976C	6.3	JDW-1572-0	44	87	P4	4500	6101	6.3	JR-5207-6	21	85	P4	4000	Triode No. 1
SD993C	6.3	JDW-1805-0	25	84	P4	3600	6101	6.3	JR-6307-5	21	85	P4	4000	Triode No. 2
SD995B	6.3	JDW-1574-0	19	73	P4	2000	6106	5.0	HR-0600-0	0	35	P3★	Plate No. 1
FM-1000	6.3	JR-2453-6	0	31	P4	750	6106	5.0	HR-0400-0	0	35	P3★	Plate No. 2
FM-1000	6.3	JR-6453-2	0	42	P4	900	6110	6.3	JDW-0507-4	0	74	P1★	Diode No. 1
1005	6.3	GX-0305-0	0	96	P5★	6110	6.3	JDW-0102-4	0	74	P1★	Diode No. 2
1005	6.3	GX-0503-0	0	96	P5★	6111	6.3	JDW-7805-0	26	86	P4	4000	Triode No. 1
SN1006	6.3	FT-4102-0	19	62	P4	1400	6111	6.3	JDW-2104-0	26	86	P4	4000	Triode No. 2
CK1027	AP-0807-0	0	91	P5★	6112	6.3	JDW-7805-0	20	65	P4	1500	Triode No. 1
CK1042	AP-0105-0	0	40	P2★	6112	6.3	JDW-2104-0	20	65	P4	1500	Triode No. 2
E1148	6.3	JR-0007-0	0	75	P4	2200	6113	6.3	JX-4506-1	7	58	P4	1250	Triode No. 1
1201	8.3	JS-1304-0	17	81	P4	3000	6134	6.3	JR-4765-3	0	88	P4	5000	
1203	6.3	JR-0407-0	0	70	P1★	6135	6.3	JR-6307-0	25	75	P4	2200	
1204	6.3	HS-5314-0	0	67	P4	1600	6136	6.3	JR-3567-2	11	76	P4	2300	
1229	2.0	JR-0230-0	20	20	640	6137	6.3	JR-4765-3	12	73	P4	2000	
1230	2.0	JR-3200-0	43	42	P4	900	6145	6.3	JR-6237-4	0	89	P4	5500	
1231	6.3	JR-6237-4	16	78	P4	2500	6146	6.3	JR-5032-7	23	91	P4	7000	Cap=P
1232	6.3	JR-6237-4	20	73	P4	2000	6152	6.3	EV-3102-0	28	86	P4	4000	
1237	2.5	JR-0300-0	0	77	P3★	6159	25.0	JR-5032-7	23	91	P4	7000	Cap=P
1237	2.5	JR-0600-0	0	77	P3★	6169	6.3	JDW-1204-0	15	86	P4	4000	
1247	0.6	EV-0000-0	0	0	P1★	6184	6.3	JDW-0204-8	0	78	P1★	Diode No. 1
HY1269	12.6	JR-3024-0	0	85	P4	4000	6184	6.3	JDW-0705-8	0	78	P1★	Diode No. 2
Short on 1 for testers having serial numbers above 135-, 136-, or 138-10000							6186	6.3	JR-3562-0	0	85	P4	4000	
1273	6.3	JR-6237-4	22	60	P4	1300	6197	6.3	EV-2631-7	0	90	P4	6000	
1274	6.3	JR-0507-3	0	33	P3★	6201	12.6	EV-7608-0	10	85	P4	4000	Triode No. 1
1274	6.3	JR-0307-5	0	33	P3★	6202	6.3	JR-0607-3	0	20	P3★	Plate No. 1
1280	12.6	JR-6237-4	22	60	P4	1300	6202	6.3	JR-0307-6	0	20	P3★	Plate No. 2
1284	12.6	JR-6237-4	23	73	P4	2000	6203	6.3	EV-0907-1	0	37	P3★	Plate No. 1
285	25.0	JR-5347-0	33	88	P4	5000	6203	6.3	EV-0107-9	0	37	P3★	Plate No. 2
291	2.5	BY-6700-0	27	65	P4	1500	6205	6.3	JDW-1572-4	19	78	P4	2500	
291	2.5	JR-3200-0	27	65	P4	1500	6211	12.6	EV-7608-2	24	84	P4	3600	Triode No. 1
293	1.5	JR-6200-0	28	60	P4	1300	6211	12.6	EV-2103-7	24	84	P4	3600	Triode No. 2
294	1.5	JR-0407-0	0	40	P1★	6216	6.3	EV-2173-0	20	92	P4	9000	
299	2.5	JR-6230-0	36	74	P4	2100	6247	6.3	JDW-2805-0	11	73	P4	2000	
SR1553D	6.3	JR-2305-0	0	89	P4	5300	6265	6.3	JR-3562-7	12	73	P4	2000	
1603	6.3	JR-0235-4	20	57	P4	1225	6293	6.3	JR-5032-0	24	90	P4	6500	Cap=P
1609	1.1	JR-3240-0	0	27	700	6350	12.6	EV-8607-3	26	87	P4	4600	Triode No. 1
1612	6.3	JR-0347-5	23	21	P4	650	6350	12.6	EV-3102-8	26	87	P4	4600	Triode No. 2
1612	6.3	JR-5347-2	23	21	P4	650	6355	6.3	FR-3827-0	0	P4	{Eye 1 Open Eye 2 Closed Eye 2 Open Eye 1 Closed
1613	6.3	JR-5347-0	23	73	P4	2000	6355	6.3	FR-8327-0	0	P4	
1614	6.3	JR-5347-2	17	88	P4	5000	6386	6.3	KR-7608-5	24	86	P4	4000	Triode No. 1
1616	4.3	JR-0000-0	0	48	P2★	6386	6.3	KR-3402-5	24	86	P4	4000	Triode No. 2
1619	2.5	JR-5340-7	12	83	P4	3400	6397	2.5	HR-8360-0	33	72	P4	1950	
1620	6.3	JR-0347-5	20	57	P4	1225	6417	12.6	EV-9167-3	0	88	P4	5000	
1621	6.3	JR-5347-0	23	73	P4	2000	6463	12.6	EV-8607-1	25	88	P4	5200	Triode No. 1
1622	6.2	JR-5347-0	17	88	P4	5000	6463	12.6	EV-3102-6	25	88	P4	5200	Triode No. 2
1623	6.3	JR-3000-0	0	75	P4	2200	6485	6.3	JR-3567-2	0	88	P4	5000	
1624	2.5	JR-3020-0	0	82	P4	3200	6660	6.3	JR-3567-2	0	79	P4	2700	
1625	12.6	JR-4036-0	25	85	P4	3800	6661	6.3	JR-3562-7	12	73	P4	2000	
1626	12.6	JR-5307-0	46	74	P4	2100	6662	6.3	JR-3562-7	0	78	P4	2500	
1629	12.6	JR-5407-0	P4	6663	6.3	JR-0703-6	0	78	P1★	Diode No. 1
1629	12.6	JR-5437-0	P4	6663	6.3	JR-0205-6	0	78	P1★	Diode No. 2
1631	12.6	JR-5347-2	17	88	P4	5000	6669	6.3	JR-3562-0	10	86	P4	4100	
1632	12.6	JR-5347-0	0	92	8000	6677	6.3	EV-2631-7	0	90	P4	6000	
1633	25.0	JX-4506-0	23	79	P4	2600	6678	6.3	EV-2637-0	7	80	P4	2800	Pent. Sect.
1633	25.0	JX-2103-0	23	79	P4	2600	6678	6.3	EV-9108-0	12	90	P4	6200	Triode Sect.
1634	12.6	JX-4506-2	0	60	P4	1325	6679	12.6	EV-7608-0	10	85	P4	4000	Triode No. 1
1634	12.6	JX-3106-2	0	60	P4	1325	6679	12.6	EV-2103-0	10	85	P4	4000	Triode No. 2
1635	6.3	JR-4307-0												