

# **MANUAL**

of  
**electronic  
tubes**

RECEIVING TUBES  
PICTURE TUBES  
CATHODE-RAY TUBES  
RECTIFIER TUBES  
TRANSMITTING TUBES  
MODULATING TUBES  
IMPULSE TUBES  
KLYSTRONS  
MAGNETRONS  
TRAVELLING WAVE TUBES  
CARCINOTRONS  
TR AND ATR SWITCH TUBES  
VACUUM CONDENSERS  
SPECIAL TUBES  
CAMERA TUBES  
SEMICONDUCTOR DIODES  
SEMICONDUCTOR RECTIFIERS  
SEMICONDUCTOR PHOTODIODES  
A. F. TRANSISTORS  
H. F. TRANSISTORS  
POWER TRANSISTORS  
INTEGRATED CIRCUITS

**MANUAL  
OF ELECTRONIC TUBES**

**TESLA**

1969

**TESLA ROŽNOV**

Editor:



**TESLA ROŽNOV**, národní podnik  
dokumentace a propagace  
**ROŽNOV POD RADHOŠTĚM**


Printed in Czechoslovakia  
MTZ, Ostrava 1

This manual of TESLA electronic tubes and semi-conductor devices contains all basic technical data required for general information. It does not list detailed data required for the development and design of new electronic instruments. A concise catalogue of tubes compiled specially for the use of designers contains, in addition to all data, also the characteristics.


This catalogue is printed on loose leaves and is kept up-to-date by additions. Receiving tubes intended for use in newly designed receivers, instruments, etc., are listed in a table of preferred types.

**KOVO**, Foreign Trade Co.,  
Dept. 8, Prague 7  
Czechoslovakia

Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings	
		Static data							
<b>1AF33</b> <b>1AF34</b>	Size max $\varnothing 19 \times 49$ mm	<b>1AF33</b>		<b>AF resistance-coupled amplifier</b>				<b>Pentode</b>	
		$U_f$ 1,4 V $I_f$ 25 mA Direct heating	$U_b$ 45 $R_a$ 1 $R_{g2}$ 3,3 $R_{g1}$ 10 $R_{g1}'$ 2,2 $I_b$ 0,05 $U_o/U_i$ 45 $k$ 2 $U_o$ 5	$67,5$ $1$ $3,3$ $10$ $2,2$ $0,075$ $60$ $3$ $5$	$90$ V $1$ M $\Omega$ $3,3$ M $\Omega$ $10$ M $\Omega$ $2,2$ M $\Omega$ $0,1$ mA $67$ $5$ V	$U_{a0}$ 250 V $U_a$ 90 V $U_{g20}$ 250 V $U_{g2}$ 67,5 V $U_{g1}$ 0 V $I_k$ 4,5 mA $R_{g1}$ 3 M $\Omega$ $R_{g1}^{1)}$ 22 M $\Omega$ $U_f$ 1,6 V $U_f$ >1,1 V			
 		$U_a$ 67,5 V $U_{g2}$ 67,5 V $U_{g1}$ -1 V $I_a$ 1,4 mA $I_{g2}$ <0,4 mA $S^{1)}$ >0,3 mA/V $R_i$ 0,6 M $\Omega$ $\mu$ 300 $I_d$ >0,1 mA $U_d$ 3 V		<b>AF resistance-coupled amplifier triode connection</b>				<b>Diode</b>	
		$1) U_{g1} = -0,5$ V <b>Capacitances</b> $C_{g1}$ 2,4 pF $C_a$ 4,6 pF $C_{a/g1}$ <0,3 pF $C_{d/f}$ 1,5 pF	$U_b$ 90 $R_a$ 0,22 $R_{g1}$ 10 $R_{g1}'$ 0,68 $U_b$ 0,25 $U_o/U_i$ 11 $k$ 1 $U_o$ 5	$90$ V $0,47$ M $\Omega$ $10$ M $\Omega$ $1,5$ M $\Omega$ $0,13$ mA $11,6$ $0,8$ % $5$ V	$90$ V $0,47$ M $\Omega$ $10$ M $\Omega$ $1,5$ M $\Omega$ $0,13$ mA $11,6$ $0,8$ % $5$ V	$U_d$ sp 50 V $I_d$ 0,2 mA $I_d$ sp 1,2 mA  $1) U_{g1}$ produced by $R_{g1}$			
Diode - AF pentode, AF amplifier, AM demodulator		<b>1AF34</b>						<b>1AF34</b>	
		$U_f$ 1,2 V $I_f$ 30 mA Direct heating						$U_f$ 1,4 V $U_f$ >0,9 V	

Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings	
		Static data							
<b>1F33</b> <b>1F34</b>	Size max $\varnothing 19 \times 49$ mm	<b>1F33</b> $U_f$ 1,4 V $I_f$ 25 mA Direct heating  $U_a$ 67,5 V $U_{g2}$ 67,5 V $U_{g1}$ -1 V $I_a$ 2,5 mA $I_{g2}$ <1,3 mA $S^{1)}$ >0,6 mA/V $R_i$ >250 k $\Omega$ $\mu$ 400	<b>1F33</b> $U_a$ 45 $U_{g2}$ 45 $U_{g1}$ 0 -10 $I_a$ 1,7 - $I_{g2}$ 0,7 - $S$ 0,65 0,01 $R_i$ 0,35 >10 $\mu_{g2/g1}$ 22 -	<b>RF and IF amplifier</b> $U_a$ 67,5 V $U_{g2}$ 67,5 V $U_{g1}$ 0 -16 V $I_a$ 3,4 - mA $I_{g2}$ 1,5 - mA $S$ 0,75 0,01 mA/V $R_i$ 0,25 >10 M $\Omega$ $\mu_{g2/g1}$ 22 -	$U_{a0}$ 150 V $U_a$ 90 V $U_{g20}$ 150 V $U_{g2}$ 67,5 V $I_k$ 5,5 mA $U_{g1}$ 0 V $W_a$ 0,3 W $W_{g2}$ 0,1 W $R_{g1}$ 3 M $\Omega$ $U_f$ 1,6 V $U_f$ >1,1 V	Capacitances $C_{g1}$ 4,2 pF $C_a$ 7,5 pF $C_c/g_1$ <0,012 pF			
Variable-mu pentode RF, IF amplifier		$U_{g1} = -0,5$ V  <b>1F34</b> $U_f$ 1,2 V $I_f$ 30 mA Direct heating	$U_a$ 90 V $U_{g2}$ 45 V $U_{g1}$ 0 -10 V $I_a$ 1,8 - mA $I_{g2}$ 0,65 - mA $S$ 0,7 0,01 mA/V $R_i$ 0,8 >10 M $\Omega$ $\mu_{g2/g1}$ 22 -	$U_a$ 90 V $U_{g2}$ 67,5 V $U_{g1}$ 0 -16 V $I_a$ 3,5 - mA $I_{g2}$ 1,4 - mA $S$ 0,75 0,01 mA/V $R_i$ 0,5 >10 M $\Omega$ $\mu_{g2/g1}$ 22 -	<b>1F34</b> $U_f$ 1,4 V $U_f$ >0,9 V				



Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings	
		Static data							
<b>1H33</b> <b>1H34</b>	Size max Ø 19×49 mm	<b>1H33</b>		<b>Mixer</b>				<b>U<sub>ao</sub></b>	250 V
		<b>U<sub>f</sub></b>	1,4 V	<b>U<sub>a</sub></b>	45	67,5	V	<b>U<sub>a</sub></b>	90 V
		<b>I<sub>f</sub></b>	25 mA	<b>U<sub>g2+4</sub></b>	45	67,5	V	<b>U<sub>g2+4o</sub></b>	90 V
		Direct heating		<b>R<sub>g1</sub></b>	100	100	kΩ	<b>U<sub>g2+4</sub></b>	67,5 V
			●	<b>I<sub>g1</sub></b>	150	250	μA	<b>U<sub>g3</sub></b>	0 V
		<b>U<sub>a</sub></b>	90 V	<b>U<sub>g3</sub></b>	0 -9	0 -14	V	<b>I<sub>k</sub></b>	5,5 mA
		<b>U<sub>g3</sub></b>	-0,5 V	<b>I<sub>a</sub></b>	0,57	1,4	mA	<b>R<sub>g3</sub></b>	3 MΩ
		<b>U<sub>g2+4</sub></b>	67,5 V	<b>I<sub>g2+4</sub></b>	1,8	3,2	mA	<b>U<sub>f</sub></b>	1,6 V
		<b>U<sub>g1</sub></b>	-0,5 V	<b>S<sub>c</sub></b>	235	5	μA/V	<b>U<sub>f</sub></b>	>1,1 V
		<b>I<sub>a</sub></b>	3,2 mA	<b>R<sub>i</sub></b>	0,6	>10	MΩ	<b>Capacitances</b>	
		<b>I<sub>g2+4</sub></b>	4,0 mA	<b>I<sub>k</sub></b>	2,5	5	mA	<b>C<sub>g1</sub></b>	3,8 pF
		<b>S<sub>g1/g2+g4</sub></b>	>0,45 mA/V	<b>U<sub>a</sub></b>	90	90	V	<b>C<sub>g3</sub></b>	6,2 pF
		<b>R<sub>i</sub></b>	>250 kΩ	<b>U<sub>g2+4</sub></b>	45	67,5	V	<b>C<sub>a</sub></b>	9 pF
				<b>R<sub>g1</sub></b>	100	100	kΩ	<b>C<sub>g2+4</sub></b>	12,5 pF
				<b>I<sub>g1</sub></b>	150	250	μA	<b>C<sub>a/g1</sub></b>	<0,1 pF
				<b>U<sub>g3</sub></b>	0 -9	0 -14	V	<b>C<sub>a/g3</sub></b>	<0,4 pF
				<b>I<sub>a</sub></b>	0,8	1,6	mA	<b>C<sub>g1/g2</sub></b>	<0,2 pF
				<b>I<sub>g2+4</sub></b>	1,9	3,2	mA	<b>1H34</b>	
				<b>S<sub>c</sub></b>	250	5	μA/V	<b>U<sub>f</sub></b>	1,4 V
				<b>R<sub>i</sub></b>	0,8	>10	MΩ	<b>U<sub>f</sub></b>	>0,9 V
				<b>I<sub>k</sub></b>	2,75	5	mA		
		<b>1H34</b>							
		<b>U<sub>f</sub></b>	1,2 V						
		<b>I<sub>f</sub></b>	30 mA						
		Direct heating							



Variable- $\mu$   
heptode  
Mixer




Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings	
		Static data					
1H35	Size max Ø 19×49 mm	$U_f$	1,4 V	Mixer		$U_f$	1,6 V
		$I_f$	25 mA	$U_a$	64 85 V	$U_f$ min	1,1 V
		Direct heating		$U_{g3}$	0 0 V	$U_a$	90 V
		●		$R_{g2}$	18 33 kΩ	$W_a$	0,15 W
		$U_a$	67,5 V	$R_{g4}$	0 120 kΩ	$U_{g4}$	67,5 V
		$U_{g4}$	45 V	$R_{g1/f}$	27 27 kΩ	$W_{g4}$	0,03 W
		$U_{g3}$	-0,5 V	$U_{g2}$	35 35 V	$U_{g3}$	0 V
		$U_{g2}$	45 V	$U_{g4}$	64 68 V	$U_{g2}$	67,5 V
		$U_{g1}$	-0,5 V	$U_{g1\text{ ef}}$	4 4 V	$W_{g2}$	0,1 W
		$I_a$	1,9 mA	$I_a$	0,55 0,6 mA	$U_{g1}$	0 V
		$I_{g4}$	<1 mA	$I_{g2}$	1,6 1,5 mA	$I_k$	3 mA
		$I_{g2}$	1,85 mA	$I_{g4}$	0,12 0,14 mA	$R_{g3/f}$	3 MΩ
		$S_{g1/g2}$	0,4 mA/V	$I_k$	2,45 2,4 mA	$R_{g1/f}$	0,1 MΩ
				$I_{g1}$	85 85 μA	Capacitances	
				$S_c$	130 160 μA/V	$C_{g3}$	6,5 pF
				$R_i$	0,9 1 MΩ	$C_a$	12 pF
				$U_{g3} (S_c - 2 \mu A/V)$	-4,5 -6,5 V	$C_{a/g3}$	<0,4 pF




Variable- $\mu$   
heptode  
Mixer

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings		
		Static data							
<b>1L33</b> <b>1L34</b>	Size max $\varnothing 19 \times 49$ mm	<b>1L33</b>		<b>AF power amplifier class A</b>			$U_{a0}$	250 V	
		$U_f$	1,4 V	$U_a$	45	67,5	90 V	$U_a$	90 V
		$I_f$	50 mA	$U_{g2}$	45	67,5	67,5 V	$U_{g20}$	250 V
		Direct heating		$U_{g1}$	-4,5	-7	-7 V	$U_{g2}$	67,5 V
				$I_a$	3,8	7,2	7,4 mA	$W_a$	0,7 W
		$U_a$	90 V	$I_{g2}$	0,8	1,5	1,4 mA	$W_{g2} (U_{g1} \sim -0 V)$	0,12 W
		$U_{g2}$	67,5 V	S	1,25	1,3	1,4 mA/V	$W_{g2} (U_{g1} - \text{max})$	0,2 W
		$U_{g1}$	-7 V	$R_a$	8	5	8 k $\Omega$	$I_k (U_{g1} \sim -0 V)$	9 mA
		$I_a$	7,5 mA	$U_{g1 \text{ ef}}$	3,2	5	5 V	$I_k (U_{g1} \sim \text{max})$	12 mA
		$I_{g2}$	1,5 mA	$P_o$	65	160	230 mW	$R_{g1}$	2 M $\Omega$
		S	1,4 mA/V	k	12	10	12 %	$U_f$	1,6 V
		$R_i$	100 k $\Omega$	<b>AF push-pull power amplifier, class B</b>			$U_f$	>1,1 V	
		$\mu$	140	$U_b$		90	V	<b>Capacitances</b>	
		$I_{ax} (U_{g1} = -15 V)$	<0,6 mA	$U_a$		80	V	$C_{g1}$	5 pF
				$U_{g2}$		57,5	V	$C_a$	6 pF
				$U_{g1}$		-9,9	V	$C_{a/g1}$	<0,45 pF
				$R_{a-a'}$		16	k $\Omega$	<b>1L34</b>	
				$U_{g1 \text{ ef}}$	0	7,3	V	$U_f$	1,4 V
				$I_a$	$2 \times 1,5$	$2 \times 4,4$	mA	$U_f$	>0,9 V
				$I_{g2}$	$2 \times 0,3$	$2 \times 1,35$	mA		
				$P_o$	0	325	mW		
				k	-	5	%		
		<b>1L34</b>							
		$U_f$	1,2 V						
		$I_f$	60 mA						
		Direct heating							




Output pentode  
Power amplifier

Type Application	Dimensions Base	Heating		Operational Data	Maximum Ratings	
		Static data				
<b>1Y32</b> <b>1Y32T</b>	Size M 4	<b>1Y32</b> $U_f$ 1,4 V $I_f$ 265 mA Direct heating Thoriated tungsten cathode		Half-wave HT rectifier $U_{SS}$ max 8 kV ( $I_{SS} = 2$ mA) $U_{SS}$ max 10 kV $Z_{trafo}$ 500 k $\Omega$ $C_N$ ( $f = 50$ c/s) 50 kpF $C_N$ (vf) 500 pF	$U_{inv}$ 20 kV $I_{sp}$ 10 mA $I_{SS}$ 2 mA $f$ 300 kc/s	
		$I_a$ 4 mA $U_a$ 45 V				To be replace by 1Y32T
		<b>1Y32T</b> $U_f$ 1,4 V $I_f$ 265 mA Direct heating Oxide-coated filament			$U_f$ 1,7 V $U_f$ min 1,1 V $U_{inv}$ 20 kV $U_{SS}$ 15 kV $I_{SS}$ 0,2 mA $C_N$ 2500 pF	
		$I_a$ >5 mA $U_a$ 150 V			Capacitances $C_{a/k}$ 1,5 pF	






HT diode  
 Half-wave rectifier  
 for TV receiver HT  
 sources


Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings		
		Static data								
3L31	Size max Ø 19,49 mm	$U_f$	2,8 V	<b>AF power amplifier, class A</b>				<b>AF amplifier</b>		
		$I_f$	50 mA	$U_f$	1,4	1,4	V	$U_a$	150 V	
		$U_f$	1,4 V	$U_a$	135	150	V	$U_{g2}$	90 V	
		$I_f$	100 mA	$U_{g2}$	90	90	V	$W_a$	2 W	
		Indirect heating		$U_{g1}$	-8	-8,8	V	$W_{g2}$	0,4 W	
		$U_a$	150 V	$U_{g1\ ef}$		0 5,5	0 6	V	$I_k$	18 mA
		$U_{g3}$	0 V	$I_{g2}$	2,8	3,5	2,2 3,5	mA	$R_{g1\ 1)}$	0,7 MΩ
		$U_{g2}$	90 V	$I_a$	14,8	15	14,2 14,2	mA	$R_{g1\ 2)}$	0,5 MΩ
		$U_{g1}$	-8,5 V	S	2,1	2,1	mA/V	1) $U_{g1}$ automatic		
		$I_a$	14 mA	$R_i$	44	50	kΩ	2) $U_{g1}$ fixed		
		$I_{g2}$	2,2 mA	$R_a$	8	8	kΩ	<b>RF amplifier</b>		
		S	1,9 mA/V	$P_o$	0,6	0,7	W	$U_a$	150 V	
		$R_i$	100 kΩ	k	10	10	%	$U_{g2}$	135 V	
		$\mu$	190	<b>RF power amplifier - <math>f = 10</math> Mc/s</b>				$U_{g1}$	-30 V	
		<b>Capacitances</b>		$U_f$	1,4	V	$I_a$	20 mA		
		$C_{g1}$	4,2 pF	$U_a$	150	V	$I_{g1}$	0,25 mA		
		$C_a$	4,9 pF	$U_{g2}$	135	V	$I_k$	25 mA		
		$C_{a/g1}$	<0,38 pF	$R_{g1}$	0,2	MΩ	$W_{g2}$	0,9 W		
				$I_a$	18,5	mA	$W_a$	2 W		
				$I_{g2}$	6,5	mA				
				$I_{g1}$	0,13	mA				
				$P_o$	1	W				






Pentode  
AF, RF power  
amplifier



Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6B31 6B32	Size M 1	$U_f$	6,3 V	Half-wave rectifier			Each section	
		$I_f$	0,3 A					
		$I_f$	0,3 A	$U_a ef$	150	V	$U_{inv}$	420 V
		$U_f$	6,3 V	$R_o$	300	$\Omega$	$I_{sp}$	54 mA
		Indirect heating		$I_{ss}$	9	mA	$I_{ss}$	9 mA
		$\bullet$		$I_{sp}$	54	mA	$W_a$	0,5 W
		$U_a$	4 V	Full-wave rectifier			$U_{k/f}$	300 V
		$I_a$	>10 mA	$U_a ef$	2×150	V	$R_{k/f}$	20 $k\Omega$
				$R_o$	2×300	$\Omega$	CN	8 $\mu F$
				CN	8	$\mu F$	$R_o$	>300 $\Omega$
				$R_z$	10	$k\Omega$		
				$I_{ss}$	>17	mA		
				Capacitances				
				$C_{aI/kI+s+f}$	3,2	pF		
				$C_{aII/kII+s+f}$	3,2	pF		
				$C_{kI/aI+s+f}$	3,6	pF		
				$C_{kII/aII+s+f}$	3,6	pF		
				$C_{aI/aII}$	<0,05	pF		
								
								
			<b>6B31</b>					
Twir. diode with separate cathodes AM, FM demodulator, ratio detector, full-wave rectifier								

Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings		
		Static data								
6BC32 EBC91	Size M 3	$U_f$	6,3 V	<b>AF resistance-coupled amplifier</b>				<b>Triode</b>		
		$I_f$	0,3 A					$U_b$	180	300
		$I_f$	0,3 A	$R_a$	0,22	0,22	0,47	$M\Omega$	$U_a$	330 V
		$U_f$	6,3 V	$R_k$	3,9	3,1	5,9	$k\Omega$	$W_a$	0,5 W
		Indirect heating		$R_{g1}$	1	1	1	$M\Omega$	$+U_{g1}$	0 V
			●	$R_{g1}'$	1	1	2,2	$M\Omega$	$-U_{g1}$	-50 V
		$U_a$	250 V	$C_k$	1,8	2,1	1,1	$\mu F$	$R_{g1} (p)$	1 $M\Omega$
		$U_{g1}$	-2 V	$C_v$ 1)	3	3	2	kpF	$R_{g1}$	3 $M\Omega$
		$I_a$	1 mA	$U_a sp$	39	79	92	V	$R_{g1} 1)$	10 $M\Omega$
		$S$	1,55 mA/V	$V$	63	68	75		$R_{k/f}$	20 $k\Omega$
		$\mu$	100	1) Coupling capacitor				$U_{k/1}$	90 V	
		$R_i$	62,5 $k\Omega$	<b>Kapacitances</b>				$I_k$	8 mA	
		$I_{az} (U_{g1} = -4,5 V)$	<0,15 mA	$C_{g1}$		2	pF	<b>Diodes</b>		
		$U_d$	4 V	$C_a$		0,65	pF	$U_d sp$	90 V	
		$I_d$	>0,15 mA	$C_{a/g1}$		2	pF	$I_d$	1 mA	
				$C_{d/g1}$		<0,04	pF	$I_d sp$	6 mA	
				$C_{d/k}$		<1,2	pF	1) $U_{g1}$ produced by $R_{g1}$		
AF triode-twin diode AF resistance-coupled amplifier and RF rectifier										



Type Application	Dimensions Base	Heating	Operational Data			Maximum Ratings	
		Static data					
6CC10	Size O 1	$U_f$ 6,3 V $I_f$ 0,6 A Indirect heating 	AF resistance - coupled amplifier			$U_{a0}$ 330 V	
		$U_a$ 250 V $U_{g1}$ -8 V $I_a$ 9,5 mA $S$ 2,6 mA/V $\mu$ 20 $R_i$ 7,7 k $\Omega$ $I_{az}$ ( $U_{g1} = -24$ V) $< 0,005$ mA	$U_b$ 180 V $R_a$ 0,1 M $\Omega$ $R_k$ 3,23 k $\Omega$ $R_{g1}$ 1 M $\Omega$ $R_{g1}'$ 0,5 M $\Omega$ $C_k$ 1,15 $\mu$ F $C_v$ 6 kpF $U_a$ sp 38 V $V$ 14	300 V 0,1 M $\Omega$ 2,44 k $\Omega$ 1 M $\Omega$ 0,25 M $\Omega$ 1,42 $\mu$ F 12,5 kpF 56 V 14	$U_a$ 275 V $W_a$ 2,75 W $U_{g1}$ min -0,5 V $U_{g1}$ -100 V $R_{g1}$ 2 M $\Omega$ $I_k$ 10 mA $U_{k/f}$ 100 V $R_{k/f}$ 20 k $\Omega$ $I_{g1}$ 2 mA		
			<b>Capacitances</b> Triode I II $C_{g1}$ 2,1 1,85 pF $C_a$ 2,5 2,4 pF $C_{a/g1}$ 3,6 3,6 pF				
			Only for information. - No on stock!				
Twin triode with separate cathodes AF amplifier							



Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings	
		Static data					
6CC31 ECC91	Size M 2	$U_f$ 6,3 V $I_f$ 0,45 A Indirect heating $U_a$ 100 V $-U_{g1}$ 0,85 V $I_a$ 8,5 mA $S$ 5,3 mA/V $\mu$ 38 $R_i$ 7,1 k $\Omega$	RF amplifier, class C $U_a$ 150 V $U_{g1}$ -10 V ( $R_{g1}$ 625 $\Omega$ or $R_k$ 220 $\Omega$ ) $I_{aI+II}$ 30 mA $I_{g1I+g1II}$ 16 mA $P_i$ 0,35 W $P_o$ 3,5 W	Mixer $U_a$ 150 V $R_k$ 800 $\Omega$ $I_a$ 4,8 mA $S_c$ 1,9 mA/V $R_i$ 10,2 k $\Omega$ $U_{osc\ ef}$ 3 V $R_{g1}$ 0,5 M $\Omega$	$U_{10}$ 500 V $U_a$ 300 V $W_a$ 1,5 W $I_a$ 15 mA $I_{g1}$ 8 mA $R_{y1}$ (k) 0,5 M $\Omega$ $U_{g1}$ -40 V $U_k/I$ 100 V $\lambda$ min 0,5 m $R_k$ >50 $\Omega$	Phase inverter $U_b$ 250 V $R_{aI}$ 25 k $\Omega$ $R_{aII}$ 25 k $\Omega$ $R_k$ 200 $\Omega$ $C_k$ 100 $\mu$ F $R_{g1I}$ 0,5 M $\Omega$ $R_{g1II}$ 25 k $\Omega$ $I_{aI+II}$ 10 mA	Capacitances 1) $C_{g1}$ 2,2 pF $C_a$ 0,55 pF $C_a/g1$ 1,6 pF
							1) Without screening




Twin triode  
 RF, AF amplifier,  
 oscillator, mixer,  
 phase inverter





Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings		
		Static data								
6CC41	Size N 1	$U_f$	6,3 V	<b>AF resistance-coupled amplifier</b>				$U_{ao}$	500 V	
		$I_f$	0,3 A	$U_b$	180	300	300	V	$U_a$	300 V
		Indirect heating		$R_a$	0,22	0,22	0,47	$M\Omega$	$W_a$	1 W
		$U_a$	250 V	$R_k$	3,5	2,8	5,2	$k\Omega$	$R_{g1}(k)$	2 $M\Omega$
		$I_a$	2,3 mA	$R_{g1}$	1	1	1	$M\Omega$	$R_{g1}^{1)}$	10 $M\Omega$
		S	2 mA/V	$R_{g1}'$	0,47	0,47	1	$M\Omega$	$I_k$	10 mA
		$\mu$	100	$C_k$	2,1	2,3	1,3	$\mu F$	$R_{g1}(p)$	0,5 $M\Omega$
		$R_i$	50 $k\Omega$	$C_{\nu}^{1)}$	6	6	3	kpF	$U_{k/f}$	$\pm 100$ V
		$U_{g1}$	-1,5 V	$U_{a \sim sp}$	34	69	77	V		
		$I_{az}$ ( $U_{g1} = -5,5$ )	<0,02 mA	V	59	65	73			
				1) Coupling capacitor				1) $U_{g1}$ produced by $I_{g1}$		
								<b>Capacitances</b>		
								$C_{g1}$	1,75 pF	
								$C_a$	1,0 pF	
								$C_{a/g1}$	2,2 pF	
								$C_{aI/aII}$	<0,05 pF	
								$C_{aI/g1II}$	<0,01 pF	
								$C_{aII/g1I}$	<0,01 pF	






Twin triode with separate cathodes  
AF amplifier,  
phase inverter

Type Application	Dimensions Base	Heating		Operational Data	Maximum Ratings			
		Static data						
6CC42	Size max $\varnothing 22,2 \times 55$ mm	$U_f$	6,3 V	HF and VHF amplifier	$U_{a0}$	550 V		
		$I_f$	0,35 A			$U_b$	250 V	$U_a$
		Indirect heating		$R_a$ 1)	12,5	k $\Omega$	$W_a$	1,5 W
		$U_a$	150 V	$U_a$	150	V	$I_k$	18 mA
		$R_k$	240 $\Omega$	$R_k$	240	$\Omega$	$R_{g1}$	1 M $\Omega$
		$I_a$	8 mA	$I_a$	8	mA	$U_{k/f}$	100 V
		S	5,5 mA/V	S	5,5	mA/V	Capacitances 1)	
		$\mu$	35	$R_i$	6,7	k $\Omega$	$C_{g1}$	2,2 pF
		$R_i$	6,7 k $\Omega$	1) $R_a$ shunted by $C_a = 1$ kpF			$C_a$	0,4 pF
		$I_{ax}$ ( $U_{g1} = -10$ V)	<80 $\mu$ A				$C_{a/g1}$	<1,6 pF
							$C_{aI/aII}$	<0,3 pF
							7) Without screening	
								
Twin triode with separate cathodes HF, VHF amplifier, mixer, oscillator								



Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings	
		Static data							
6F10	Size O 2	$U_f$	6,3 V	RF amplifier				$U_{an}$	550 V
		$I_f$	0,45 A	$U_b$		300 V	$U_a$	310 V	
		Indirect heating		$U_a$	300	300 V	$W_a$	3,3 W	
		$U_a$	300 V	$U_{g3}$	0	0 V	$U_{g20}$	550 V	
		$U_{g3}$	0 V	$U_{g2}$	150	V	$U_{g2}$	165 V	
		$U_{g2}$	150 V	$R_{g2}$	0	60 k $\Omega$	$W_{g2} (U_{g1} \sim -0 V)$		
		$R_k$	160 $\Omega$	$R_k$	160	160 $\Omega$	0,45 W		
		$I_a$	10,25 mA	$I_a$	10,25	10,25 mA	$W_{g2} (U_{g1} \sim \text{max})$		
		$I_{g2}$	2,2 mA	$I_{g2}$	2,5	2,5 mA	0,8 W		
		S	9 mA/V	S	9	9 mA/V	$I_k$	25 mA	
		$\mu_{g2/g1}$	50	$R_i$	300	300 k $\Omega$	$-U_{g1}$	-30 mA	
		$R_i$	300 k $\Omega$	$Z_{g1} (f=100 \text{ Mc/s})$	540	$\Omega$	$R_{g1}$	0,5 M $\Omega$	
				$R_{ekv}$	650	$\Omega$	$R_{g1}^{1)}$	0,25 M $\Omega$	
				RF amplifier, g2 and g3 connected to a				$U_{k/f}$	100 V
				$U_a$	150 V	$\mu$	40	$R_{k/f}$	20 k $\Omega$
				$R_k$	160 $\Omega$	$R_i$	3,6 k $\Omega$	Triode connection	
				$I_a$	12,5 mA			$U_a$	165 V
				S	11 mA/V			1) $U_{g1}$ fixed	
								<b>Capacitances</b>	
								$C_{g1}$	11 pF
								$C_a$	5 pF
								$C_a/g_1$	<0,015 pF
								Only for information. - No on stock!	



RF pentode  
RF, IF, wideband  
amplifier


Type Application	Dimensions Base	Static data		Operational Data	Maximum Ratings		
		Heating					
6F24	Size L 3	$U_f$	6,3 V	RF amplifier class A	$U_{a0}$	400 V	
		$I_f$	0,45 A	$U_a$	250 V	$U_a$	250 V
		Indirect heating		$U_{g3}$	0 V	$W_a$	4 W
				$U_{g2}$	200 V	$U_{g2}$	250 V
		$U_a$	250 V	$R_k$	120 Ω	$W_{g2}$	0,45 W
		$U_{g3}$	0 V	$I_a$	15 mA	$I_k$	20 mA
		$U_{g2}$	200 V	$I_{g2}$	2,1 mA	$R_{g1}$	0,5 MΩ
		$U_{g1}$	-2 V	S	10 mA/V	$U_{k/l}$	50 V
		$I_a$	15 mA	$R_i$	0,3 MΩ	Capacitances	
		$I_{g2}$	2,1 mA	$I_{ax} (U_{g1} = -7 V)$	<0,5 mA	$C_{g1}$	10,5 pF
		S	10 mA/V			$C_a$	5,9 pF
		$R_i$	0,3 MΩ			$C_{a/g1}$	<0,035 pF
		$I_{ax} (U_{g1} = -7 V)$	<0,5 mA				
							
							
RF high-slope pentode RF, IF, wideband amplifier							

Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings		
		Static data						
6F31 6BA6	Size M 2	$U_f$	6,3 V	<b>RF and IF amplifier</b>		$U_{a0}$	500 V	
		$I_f$	0,3 A	$U_a$	100	250 V	$U_i$	300 V
		Indirect heating		$U_{g3}$	0	0 V	$W_a$	3 W
		$U_a$	250 V	$U_{g2}$	100	100 V	$U_{g20}$	300 V
		$U_{g3}$	0 V	$R_k$	68	68 $\Omega$	$U_{g2}$	125 V
		$U_{g2}$	100 V	$I_a$	10,8	11 mA	$W_{g2}$	0,6 W
		$R_k$	68 $\Omega$	$I_{g2}$	4,4	4,2 mA	$-U_{g1}$	-50 V
		$I_a$	11 mA	$S$	4,3	4,4 mA/V	$R_{g1}$	3 M $\Omega$
		$I_{g2}$	4,2 mA	$R_i$	0,25	1,5 M $\Omega$	$U_{k/f}$	150 V
		$S$	4,4 mA/V	$U_{g1} (S=44 \mu A/V)$	-20	-20 V	$T_b$	150 $^{\circ}C$
		$R_i$	1,5 M $\Omega$				<b>Capacitances</b>	
		$I_{az} (U_{g1} = -20 V)$	<0,4 mA				$C_{g1}$	5,5 pF
							$C_a$	5 pF
							$C_{g/g1}$	<0,005 pF





RF variable-mu  
pentode  
RF, IF amplifier

Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings		
		Static data						
<b>6F32</b> <b>EF95</b>	Size max $\varnothing 19 \times 45,2$ mm	$U_f$	6,3 V	<b>RF amplifier, class A</b>		$U_{10}$	320 V	
		$I_f$	0,175 A	$U_a$	120	180 V	$U_a$	200 V
		Indirect heating		$U_{g2}$	120	120 V	$W_1$	1,7 W
		$U_a$	120 V	$R_k$	200	200 $\Omega$	$U_{g20}$	320 V
		$U_{g2}$	120 V	$I_a$	7,5	7,7 mA	$U_{g2}$	150 V
		$R_k$	200 $\Omega$	$I_{g2}$	2,5	2,4 mA	$w_{g2}$	0,5 W
		$I_a$	7,5 mA	S	5	5,1 mA/V	$I_k$	18 mA
		$I_{g2}$	<3,5 mA	$R_i$	0,34	0,69 M $\Omega$	$R_{g1}$	1 M $\Omega$
		S	5,2 mA/V	$Z_{g1}$ (f=50 Mc/s)	25	25 k $\Omega$	$U_{k/f}$	100 V
		$\mu_{g2/g1}$	25	$R_{ekv}$	2	2 k $\Omega$	$R_{k/f}$	20 k $\Omega$
		$R_i$	>0,25 M $\Omega$	<b>RF amplifier, class A - Triode connection</b>		<b>Capacitances</b>		
				$U_a$	120	180 V	$C_{g1}$	4,5 pF
				$U_{g1}$	-2,65	-6 V	$C_a$	2,8 pF
				$R_k$	265	925 $\Omega$	$C_a/g_1$	<0,025 pF
				$I_a$	10	6,5 mA		
				S	6	3,5 mA/V		
				$R_i$	5	6,66 k $\Omega$		
				$\mu$	30	23,3		
				$Z_{g1}$ (f=100 Mc/s)	9,5	k $\Omega$		
				$R_{ekv}$	700	$\Omega$		





RF high-slope pentode  
RF, IF, wideband  
amplifier

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6F32V	Size M 1	$U_f$	6,3 V	RF amplifier, class A			$U_a$	200 V
		$I_f$	0,175 A	$U_a$	120	180 V	$W_a$	1,8 W
		Indirect heating		$U_{g2}$	120	120 V	$U_{g2}$	150 V
		$U_a$	120 V	$R_k$	200	200 $\Omega$	$W_{g2}$	0,55 W
		$U_{g2}$	120 V	$I_a$	7,5	7,7 mA	$I_k$	20 mA
		$R_k$	200 $\Omega$	$I_{g2}$	2,5	2,4 mA	$R_{g1}$	1 M $\Omega$
		$I_a$	$7,5 \pm 2,5$ mA	S	5,2	5,1 mA/V	$U_{k/f}$	$\pm 120$ V
		$I_{g2}$	$< 3,5$ mA	$R_i$	300	500 k $\Omega$	$R_{k/f}$	20 k $\Omega$
		S	$5,2 \pm 1,4$ mA/V	$Z_{g1}$ (f=50 Mc/s)	25	k $\Omega$	$U_f$	7 V
		$R_i$	$> 250$ k $\Omega$	$R_{ekv}$	1	k $\Omega$	$U_f$	$> 5,7$ V
		$I_{az}$ ( $R_a = 100$ k $\Omega$ )	$U_{g1} = -10$ V	High-reliability tube			<b>Capacitances</b>	
			$< 200$ $\mu$ A	Vibration and shock proofed			$C_{g1}$	$4,3 \pm 0,5$ pF
				Exacting tolerances			$C_a$	$3,4 \pm 0,6$ pF
				Stabilized			$C_{a/g1}$	$< 0,02$ pF





RF high-slope pentode  
RF, IF, wideband  
amplifier

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6F35 6AJ5	Size max ∅ 19×45,2 mm	$U_f$	6,3 V	RF and IF amplifier, class A			$U_{a0}$	250 V
		$I_f$	0,175 A	$U_a$	28 V		$U_a$	180 V
		Indirect heating		$U_{g2}$	28 V		$W_a$	1,7 W
		$U_a$	28 V	$R_k$	270 Ω		$U_{g20}$	250 V
		$U_{g2}$	28 V	$I_a$	2,7 mA		$U_{g2}$	75 V
		$U_{g1}$	-0,8 V	$I_{g2}$	1 mA		$W_{g2}$	0,5 W
		$I_a$	3 mA	$S$	2,7 mA/V		$U_{g1}$	0 V
		$I_{g2}$	1,3 mA	$R_i$	100 kΩ		$I_k$	18 mA
		$S$	2,8 mA/V				$U_{k/f}$	90 V
		$I_{az}$	( $U_{g1} = -3 V$ ) <0,5 mA				Capacitances	
							$C_{g1}$	5,5 pF
							$C_a$	2,8 pF
							$C_{a/g1}$	<0,03 pF
								
								
RF high-slope pentode RF, IF amplifier								





Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6F36 6AH6	Size M 3	$U_f$	6,3 V	<b>RF amplifier</b>			$U_{a0}$	550 V
		$I_f$	0,45 A	$U_b$	300	V	$U_a$	300 V
		Indirect heating		$U_a$	300	V	$W_a$	3,3 W
		$U_a$	300 V	$U_{g3}$	0	V	$U_{g20}$	550 V
		$U_{g3}$	0 V	$U_{g2}$	150	V	$U_{g2}$	165 V
		$U_{g2}$	150 V	$R_{g2}$	0	60 $k\Omega$	$W_{g2} (U_{g1} \sim -0 V)$	
		$R_k$	160 $\Omega$	$R_k$	160	$\Omega$	0,45 W	
		$I_a$	10,25 mA	$I_a$	10,25	10,25 mA	$W_{g2} (U_{g1} \sim \text{max})$	
		$I_{g2}$	2,2 mA	$I_{g2}$	2,2	2,2 mA	0,8 W	
		S	9 mA/V	S	9	9 mA/V	$I_k$	25 mA
		$R_i$	1 $M\Omega$	$R_i$	0,5	0,5 $M\Omega$	$-U_{g1}$	-30 V
		$I_{az} (U_{g1} = -6 V)$	<0,6 mA	<b>RF amplifier, g2 and g3 connected to a</b>			$R_{g1}$	0,5 $M\Omega$
		<b>Capacitances</b>		$U_a$	150	V	$R_{g1} 1)$	0,25 $M\Omega$
		$C_{g1}$	13,2 pF	$R_k$	160	$\Omega$	$U_{k/f}$	100 V
		$C_a$	6,5 pF	$I_a$	12,5	12,5 mA	$R_{k/f}$	20 $k\Omega$
		$C_{a/g1} 1)$	<0,015 pF	S	11	11 mA/V	Triode connection	
		1) With screening		$\mu$	40		$U_a$	165 V
				$R_i$	3,6	$k\Omega$	1) $U_{g1}$ fixed	
				$U_{g1} (I_a = 10 \mu A)$	-7	V		





RF high-slope  
pentode  
RF, IF, wideband  
amplifier

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6H31 6BE6	Size M 2	$U_f$	6,3 V	$U_a$	100	250 V	$U_{a0}$	550 V
		$I_f$	0,3 A	$U_{g2+g4}$	100	100 V	$U_a$	300 V
		Indirect heating		$U_{g3}$	-1,5	-1,5 V	$W_a$	1 W
		$U_a$	250 V	$U_{g1\ ef}$	10	10 V	$U_{g2+g40}$	300 V
		$U_{g2+g4}$	100 V	$I_a$	2,8	3 mA	$U_{g2+g4}$	100 V
		$U_{g3}$	-1,5 V	$I_{g2+g4}$	7,3	7,1 mA	$W_{g2+g4}$	1 W
		$I_{g1}$	0,5 mA	$I_{g1}$	0,5	0,5 mA	$U_{g1}$	0 V
		$I_a$	3 mA	$I_k$	10,6	10,6 mA	$U_{g1}$	-50 V
		$I_{g2+g4}$	<9,5 mA	$R_{g1}$	20	20 $k\Omega$	$U_{g3}$	0 V
		$R_{g1}$	20 $k\Omega$	$R_i$	0,5	1 $M\Omega$	$-U_{g3}$	-50 V
		$C_{g1}$	4 $\mu F$	$S_c$	0,455	0,475 mA	$I_k$	14 mA
		$U_{g1\ ef}$	10 V	$U_{g3} (S_c=10\ \mu A/V)$	-30	-30 V	$U_{k/I}$	90 V
		$f$	50 Hz	<b>Capacitances</b>			$R_{g3}$	20 $k\Omega$
		$S_c$	>0,3 mA/V	$C_{g3}$	7,15	pF		
		$U_{g3\ ef}$	0,354 V	$C_a$	8,6	pF		
				$C_{g1}$	5,5	pF		
				$C_{a/g3}$	<0,35	pF		
				$C_{g1/g3}$	<0,15	pF		
				$C_{a/g1}$	<0,06	pF		





Variable-mu heptode  
Mixer

Type Application	Dimensions Base	Static data		Operational Data		Maximum Ratings			
		Heating							
6L10	Size O 2	$U_f$	6,3 V	<b>Wideband amplifier output stage:</b>				$U_{20}$	550 V
		$I_f$	0,65 A	$U_a$	300 V	S	11 mA/V	$U_a$	330 V
		Indirect heating		$U_{g3}$	0 V	$R_i$	90 k $\Omega$	$W_a$	9 W
		$U_a$	300 V	$U_{g2}$	150 V	$R_a$	7 k $\Omega$	$U_{g20}$	550 V
		$U_{g3}$	0 V	$R_k$	80 $\Omega$	$P_o$	3,5 W	$U_{g2}$	330 V
		$U_{g2}$	150 V	$I_{a0}$	30 mA	k	10 %	$W_{g2} (U_{g1} \sim -0 V)$	
		$U_{g1}$	-3 V	$I_a$	30,5 mA	$U_{g1 ef}$	2 V	1,5 W	
		$I_a$	30 mA	$I_{g20}$	7 mA			$W_{g2} (U_{g1} \sim \text{max})$	
		$I_{g2}$	7 mA	$I_{g2}$	9 mA			3 W	
		S	11 mA/V	<b>Video amplifier output stage:</b>				$I_k$	50 mA
		$\mu_{g2/g1}$	20	$U_b$	300	300	V	$R_{g1}$	0,1 M $\Omega$
		$R_i$	90 k $\Omega$	$U_a$	145	200	V	$U_k/f$	100 V
				$U_{g3}$	0	0	V	$R_k/f$	20 k $\Omega$
				$R_{g2}$	0	25	k $\Omega$	<b>Capacitances</b>	
				$U_{g2}$	115	(125)	V	$C_{g1}$	13 pF
				$R_k$	0	57	$\Omega$	$C_a$	6,5 pF
				$R_{g1}$	0,1	-	M $\Omega$	$C_{a/g1}$	<0,06 pF
				$U_{g1}$	0	(-2)	V		
				$I_a$	45	28	mA		
				$I_{g2}$	13	7	mA		
				$R_a$	3,5	3,5	k $\Omega$		
				$U_{a \sim sp/sp}$	135	140	V		
				$U_{g1 \sim sp/sp}$	4	4	V		
				Only for information. - No on stock!					




Power pentode for wideband amplifiers

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
<b>6L31</b> <b>6AQ5</b>	Size M 2	$U_f$ 6,3 V $I_f$ 0,45 A Indirect heating	<b>AF power amplifier, class A</b>			$U_{a0}$ 500 V $U_a$ 315 V $W_a$ 12 W $U_{g20}$ 500 V $U_{g2}$ 285 V $W_{g20}$ 2,5 W $W_{g2}$ 3 W $I_k$ 60 mA $R_{g1}$ 0,5 M $\Omega$ $R_{g1}^{1)}$ 0,1 M $\Omega$ $U_{k/f}$ 100 V		
		$U_a$ 250 V $U_{g2}$ 250 V $U_{g1}$ -12,5 V $I_a$ 45 mA $I_{g2}$ <8,5 mA $S$ 4,1 mA/V $R_i$ 52 k $\Omega$ $I_{az}$ ( $U_{g1} = -30$ V) <8 mA	$U_a$ 180 250 V $U_{g2}$ 180 250 V $U_{g1}$ -8,5 -12,5 V $I_{a0}$ 29 45 mA $I_a$ 30 47 mA $I_{g20}$ 3 4,5 mA $I_{g2}$ 4 7 mA $R_i$ 58 52 k $\Omega$ $S$ 3,7 4,1 mA/V $R_a$ 5,5 5 k $\Omega$ $P_o$ 2 4,5 W $k$ 8 8 %	<b>AF push-pull amplifier, class AB</b> $U_a$ 250 V $U_{g2}$ 250 V $U_{g1}$ -15 V $I_{a0}$ 2×35 mA $I_a$ 2×39,5 mA $I_{g20}$ 2×2,5 mA $I_{g2}$ 2×6,5 mA $R_{c-a'}$ 10 k $\Omega$ $U_{g1\ ef}$ 10,5 V $P_o$ 10 W $k$ 5 %	1) $U_{g1}$ fixed  <b>Capacitances</b> $C_{a/g1}$ <0,6 pF			





Output beam tetrode  
AF power amplifier

Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings			
		Static data							
6L41	Size max Ø 22×70 mm	$U_f$	6,3 V	<b>Oscillator or power amplifier –</b> $f = 50 \text{ Mc/s}$		$U_a$	300 V	$U_a$	300 V
		$I_f$	0,75 A			$U_a$	300 V	$R_{g1}$	22 $k\Omega$
		Indirect heating		$U_{g2}$	250 V	$I_{g1}$	3 mA	$U_{g2}$	250 V
		$U_a$	300 V	$U_{g1}$	-60 V	$U_{g1 \text{ sp}}$	80 V	$W_{g2}$	2,0 W
		$U_{g3}$	0 V	$I_a$	50 mA	$W_{g1}$	0,35 W	$I_{g1}$	5 mA
		$U_{g2}$	250 V	$I_{g2}$	5 mA	$P_o$	8 W	$I_k$	55 mA
		$U_{g1}$	-6 V	<b>Frequency multiplier –</b> $f \text{ max} = 175 \text{ Mc/s}$		$I_k \text{ sp}$	100 mA	$U_{k/f}$	100 V
		$I_a$	50 mA			<b>Doubler</b>		$f$	175 Mc/s
		$I_{g2}$	5 mA	<b>Trebler</b>		$U_a$	300 V	<b>Capacitances</b>	
		$S$	7 mA/V	$U_a$	300	$U_{bg2}$	300 V	$C_{g1}$	9,5 pF
		$\mu_{g1/g2}$	16	$U_{bg2}$	300	$R_{g2}$	12,5 $k\Omega$	$C_a$	5,4 pF
		$S/C$	0,5	$R_{g1}$	12,5	$U_{g1}$	-75	$C_{a/g1}$	<0,45 pF
		$I_{az} (U_{g1} = -25 \text{ V})$	<3 mA	$U_{g1}$	-75	$I_a$	40		
				$I_a$	40	$I_{g2}$	4		
				$I_{g2}$	4	$R_{g1}$	75		
				$R_{g1}$	75	$I_{g1}$	1		
				$I_{g1}$	1	$U_{g1 \text{ sp}}$	95		
				$U_{g1 \text{ sp}}$	95	$W_{g1}$	0,6		
				$W_{g1}$	0,6	$P_o$	3,6		
				$P_o$	3,6				



Beam tetrode  
AF, RF power amplifier,  
frequency multiplier

Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings				
		Static data								
<b>6L43</b>	Size N 4	$U_f$	6,3 V	<b>Wideband amplifier output stage</b>		$U_{a0}$	550 V			
		$I_f$	0,65 A			$U_a$	300 V	S	11 mA/V	$U_{\gamma}$
		Indirect heating		$U_{g3}$	0 V	$R_i$	90 k $\Omega$	$W_a$	9 W	
		$U_a$	300 V	$U_{g2}$	150 V	$R_a$	7 k $\Omega$	$U_{g20}$	550 V	
		$U_{g3}$	0 V	$R_k$	80 $\Omega$	$P_o$	3,5 W	$U_{g2}$	330 V	
		$U_{g2}$	150 V	$I_{a0}$	30 mA	k	10 %	$W_{g2} (U_{g1\text{ ef}} = 0 \text{ V})$	1,5 W	
		$U_{g1}$	-3 V	$I_a$	30,5 mA	$U_{g1\text{ ef}}$	2 V	$W_{g2} (U_{g1\text{ ef}} \text{ max})$	3 W	
		$I_a$	30 mA	$I_{g20}$	7 mA			$I_k$	50 mA	
		$I_{g2}$	7 mA	$I_{g2}$	9 mA	<b>Video amplifier output stage</b>		$R_{g1}$	0,1 M $\Omega$	
		S	11 mA/V			$U_b$	300	300 V	$U_{k/f}$	100 V
		$\mu_{g2/g1}$	20			$U_a$	145	200 V	$R_{k/f}$	20 k $\Omega$
		$R_i$	90 k $\Omega$			$U_{g3}$	0	0 V	<b>Capacitances</b>	
		$I_{az} (U_{g1} = -20 \text{ V})$	<0,1 mA			$U_{g2}$	0	25 k $\Omega$	$C_{g1}$	11 pF
						$R_{g2}$	0	(125) V	$C_a$	5,5 pF
						$U_{g2}$	115	57 $\Omega$	$C_{a/g1}$	<0,1 pF
						$R_k$	0	- M $\Omega$		
						$R_{g1}$	0,1	28 mA		
						$I_a$	45	7 mA		
						$I_{g2}$	13	3,5 k $\Omega$		
						$R_a$	3,5	140 V		
						$U_a\text{ sp/sp}$	135	4 V		
						$U_{g1\text{ sp/sp}}$	4			






Power pentode for  
video and wideband  
amplifiers




Type Application	Dimensions Base	Heating		Operational Data		Maximum Ratings	
		Static data					
6L50S (6L50V)	Size R 2	$U_f$	6,3 V	Pulse operation		$U_a$	4500 V <sup>1)</sup>
		$I_f$	1,0 A			$U_a$	3000 V
		$t_f$	25 s	$U_{g2}$	250 V	$W_a$	18 W
		Indirect heating		$U_{g1}$	-70 V	$W_{g2}$	3 W
		$U_a$	400 V	$U_{g1\ ip}$	$a\bar{x}+20$ V	$I_k$	100 mA
		$U_{g3}$	0 V	$I_a$	330 mA	$I_k\ \delta p$	300 mA
		$U_{g2}$	250 V	$I_{g2}$	30 mA	$I_{k\ t\ 2)}$	1500 mA
		$U_{g1}$	-25 V	$I_{g1}$	30 mA	$R_{g1\ 3)}$	100 k $\Omega$
		$I_a$	30 mA			$R_{g1}$	250 k $\Omega$
		$I_{g2}$	2 mA			$U_{k/f}$	80 V
		$S$	3,5 mA/V			$R_{k/f}$	20 k $\Omega$
		$R_i$	75 k $\Omega$				
Beam tetrode AF, RF power amplifier for pulse operation						<sup>1)</sup> Pulse duration max 10 $\mu$ s, max 15 % per. <sup>2)</sup> $t_{ip} = 1 \mu$ s <sup>3)</sup> $U_{g1}$ fixed	
						<b>Capacitances</b>	
						$C_{g1}$	9,7 pF
						$C_a$	7,3 pF
						$C_{a/g1}$	<0,3 pF





Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6Y50	Size R 1	$U_f$	6,3 V	<b>Half-wave rectifier</b>			$U_{inv}$	3500 V
		$I_f$	1,65 A	$U_a \sim e_f$ 1)	1200	V	$W_a$	10 W
		$t_f$	1 min	$I_{ss}$	220	mA	$I_{ss}$	220 mA
		Indirect heating		$U_{ss}$	1350	V	$I_{sp}$	700 mA
			⊙	$R_t$	150	$\Omega$	$R_t$	>150 $\Omega$
		$U_a$	30 V	$CN$	4	$\mu F$	$U_{k/f}$	50 V
		$I_a$	>200 mA	<b>Full-wave rectifier</b>			<b>Capacitances</b>	
				$U_a \sim e_f$ 1)	2×850	V	$C_{a/k}$	5 pF
				$I_{ss}$	400	mA		
				$U_{ss}$	800	V		
				$R_t$	2×150	$\Omega$		
				$CN$	4	$\mu F$		
				1) $U_a$ must be connected after heating the cathode, otherwise $U_{inv}$ must be reduced to 2000 V.				
		 						
		HT diode Half-wave rectifier full-wave rectifier (two tubes)						

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
6Z31	Size M 3	$U_f$	6,3 V	<b>Filter input:</b>	<b>Capacitive</b>	<b>Inductive</b>	$U_{inu}$	1000 V
		$I_f$	0,6 A	$U_{a \sim ef}$	$2 \times 325$	$2 \times 450$ V	$I_{sp}$	300 mA
		Indirect heating		CN	max 4	— $\mu$ F	$I_{ss}$	70 mA
			●	$R_i$	150	— $\Omega$	$U_{k/f}$	450 V
		$I_d$	50 mA	L	—	min 8 H	CN	16 $\mu$ F
		$R_i$	250 $\Omega$	$I_{ss}$	70	70 mA		
				$U_{ss}$	355	375 V		
								
Twin diode Full-wave rectifier								

Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings		
		Static data								
12BC32	Size max $\varnothing 19 \times 57$ mm	$I_f$	150 mA	AF resistance-coupled amplifier				Triode		
		$U_f$	12,6 V	$U_b$	180	300	300	V	$U_f$	14 V
		Indirect heating		$R_a$	0,22	0,22	0,47	$M\Omega$	$U_f$	>11,4 V
		$U_a$	100 V	$R_k$	3,9	3,1	5,9	$k\Omega$	$U_{a0}$	500 V
		$U_{g1}$	-1 V	$R_{g1}$	1	1	1	$M\Omega$	$U_a$	330 V
		$I_a$	0,5 mA	$R_{g1}'$	1	1	2,2	$M\Omega$	$W_a$	0,5 W
		S	1,25 mA/V	$C_k$	1,8	2,1	1,1	$\mu F$	$+U_{g1}$	0 V
		$\mu$	100 $k\Omega$	$C_v$ 1)	3	3	2	kpF	$-U_{g1}$	-50 V
		$R_i$	80 $k\Omega$	$U_{a \sim sp}$	39	79	92	V	$R_{g1}$ 1)	3 $M\Omega$
		$U_d$	4 V	V	63	68	75		$R_{g1}'$ 1)	10 $M\Omega$
		$I_d$	>0,15 mA	1) Coupling capacitor				$R_k/f$	20 $k\Omega$	
				Capacitances				$U_k/f$	150 V	
				$C_{g1}$		2	pF	$I_k$	8 mA	
				$C_a$		0,65	pF	Diode		
				$C_{a/g1}$		2	pF	$U_d sp$	90 V	
				$C_{d/g1}$		<0,04	pF	$I_d$	1 mA	
				$C_{d/k}$		<1,2	pF	$I_d sp$	6 mA	
								1) $U_{g1}$ produced by $R_{g1}$		
Twin diode-AF triode RF rectifier AF resistance-coupled amplifier										





Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
12F31	Size M 3	$I_f$	150 mA	RF and IF amplifier			$U_{a0}$	500 V
		$U_f$	12,6 V				$U_a$	100
		Indirect heating		$U_{g3}$	0	0 V	$W_a$	3 W
		$U_a$	250 V	$U_{g2}$	100	100 V	$U_{g20}$	300 V
		$U_{g3}$	0 V	$R_k$	68	68 $\Omega$	$U_{g2}$	125 V
		$U_{g2}$	100 V	$I_a$	10,8	11 mA	$W_{g2}$	0,6 W
		$R_k$	68 $\Omega$	$I_{g2}$	4,4	4,2 mA	$U_{g1}$	0 V
		$I_a$	11 mA	$S$	4,3	4,4 mA/V	$-U_{g1}$	-50 V
		$I_{g2}$	4,2 mA	$R_i$	0,25	1,5 $M\Omega$	$R_{g1}$	3 $M\Omega$
		$R_i$	1,5 $M\Omega$				$U_{k/f}$	150 V
		$S$	4,4 mA/V				$T_b$	150 $^{\circ}C$
		$I_{az}$ ( $U_{g1} = -20 V$ )	<0,4 mA				<b>Capacitances</b>	
							$C_{g1}$	5,5 pF
							$C_a$	5 pF
							$C_{a/g1}$	<0,005 pF




Variable-mu pentode  
RF, IF amplifier



Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings		
		Static data							
12H31	Size max Ø 19×57 mm	$I_f$	150 mA	<b>Mixer</b>			$U_{a0}$	500 V	
		$U_f$	12,6 V	$U_a$	100	250	V	$U_a$	300 V
		Indirect heating		$U_{g2+g4}$	100	100	V	$W_a$	1 W
		$U_a$	250 V	$U_{g3}$	-1,5	-1,5	V	$U_{g2+g40}$	300 V
		$U_{g2+g4}$	100 V	$U_{g1\ ef}$	10	10	V	$U_{g2+g4}$	100 V
		$U_{g3}$	-1,5 V	$I_a$	2,8	3	mA	$W_{g2+g4}$	1 W
		$R_{g1}$	20 kΩ	$I_{g2+g4}$	7,3	7,1	mA	$U_{g1}$	0 V
		$I_{g1}$	0,5 mA	$I_{g1}$	0,5	0,5	mA	$-U_{g1}$	-50 V
		$I_a$	3 mA	$I_k$	10,6	10,6	mA	$U_{g3}$	0 V
		$I_{g2+g4}$	<9,5 mA	$R_{g1}$	20	20	kΩ	$-U_{g3}$	-50 V
		$R_{g1}$	20 kΩ	$R_i$	0,5	1	MΩ	$R_{g1}$	1 MΩ
		$C_{g1}$	4 μF	$S_c$	0,455	0,475	mA/V	$R_{g3}$	1 MΩ
		$U_{g1\ ef}$	10 V	$U_{g3} (S_c = 4 \mu A/V)$	-30	-30	V	$I_k$	14 mA
		$f$	50 Hz	<b>Capacitances</b>			$U_{k/f}$	150 V	
				$C_{g3}$	7,15	pF	$U_f$	14 V	
				$C_a$	8,6	pF	$U_f$	>11,4 V	
				$C_{g1}$	5,5	pF			
				$C_{a/g3}$	<0,35	pF			
				$C_{g1/g3}$	<0,15	pF			
				$C_{a/g1}$	<0,05	pF			
				$C_{g1/k}$	2,75	pF			
				$C_k$	13,5	pF			
		$I_{az} (U_{g3} = -30 V)$	<0,4 mA						




Variable- $\mu$  heptode  
Mixer

Type Application	Dimensions Base	Heating		Operational Data	Maximum Ratings		
		Static data					
18F24	Size L 3	$U_f$	18 V	RF amplifier, class A		$U_{ao}$	400 V
		$I_f$	0,165 A			$U_a$	250 V
		Indirect heating		$U_{g3}$	0 V	$W_a$	4 W
		$U_a$	250 V	$U_{g2}$	200 V	$U_{g2}$	250 V
		$U_{g3}$	0 V	$R_k$	120 $\Omega$	$W_{g2}$	0,45 W
		$U_{g2}$	200 V	$I_a$	15 mA	$I_k$	20 mA
		$U_{g1}$	-2 V	$I_{g2}$	2,1 mA	$R_{g1}$	0,5 M $\Omega$
		$I_a$	15 mA	$S$	10 mA/V	$U_{k/f}$	50 V
		$I_{g2}$	2,1 mA	$R_i$	0,3 M $\Omega$	<b>Capacitances</b>	
		$S$	10 mA/V			$C_{g1}$	10,5 pF
		$R_i$	0,3 M $\Omega$			$C_a$	5,9 pF
		$I_{az} (U_{g1} = -7 V)$	<0,5 mA			$C_{a/g1}$	<0,035 pF
							
RF high-slope pentode RF, IF, wideband amplifier							

Type Application	Base Dimensions	Heating		Operational Data				Maximum Ratings		
		Static data								
35L31	Size M 4	$I_f$	150 mA	AF power amplifier, class A				$U_{a0}$	550 V	
		$U_f$	35 V	$U_a$	100	180	200	V	$U_a$	250 V
		Indirect heating		$U_{g2}$	100	180	200	V	$W_a$	11 W
		$U_a$	200 V	$R_k$	140	140	200	$\Omega$	$U_{g20}$	550 V
		$U_{g2}$	200 V	$I_a$	32,5	61	55	mA	$U_{g2}$	250 V
		$U_{g1}$	-13 V	$I_{g2}$	5,5	10	9,5	mA	$W_{g2} (U_{g1} \sim 0 V)$	1,9 W
		$I_a$	55 mA	S	7,5	9	8	mA/V	$W_{g2} (U_{g1} \sim \max)$	3,5 W
		$I_{g2}$	9,5 mA	$R_i$	25	22	25	$k\Omega$	$R_{g1}$	1 $M\Omega$
		S	8 mA/V	$R_a$	3	3	3,5	$k\Omega$	$U_{k/f}$	150 V
		$R_i$	25 $k\Omega$	$P_o$	1,35	4,8	4,8	W	$R_{k/f}$	20 $k\Omega$
		$I_a (U_{g1} = -28 V)$	<10 mA	k	10	10	10	%	$U_f$	38,5 V
				$U_{g1\ ef}$	3,8	6,2	6,2	V	$U_f$	>31,5 V
				$U_{g1\ ef} (P_o = 50\ mW)$	0,55	0,5	0,5	V	Capacitances	
									$C_a/g_1$	<1,2 pF




Output pentode  
AF power amplifier


Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
35Y31	Size M 4	$I_f$	150 mA	$U_{a\ ef}$	127-170	170-250 V	$U_{inv}$	700 V
		$U_f$	35 V	$R_o$ ( $C_N=60\ \mu F$ )	100	175 $\Omega$	$U_{a\ ef}$	250 V
		Indirect heating		( $C_N=32\ \mu F$ )	75	125 $\Omega$	$I_{ss}$	140 mA
				( $C_N=16\ \mu F$ )	30	75 $\Omega$	$I_{sp}$	850 mA
				( $C_N=8\ \mu F$ )	0	0 $\Omega$	$W_a$	2,5 W
				$C_N$	32	32 $\mu F$	$U_{k/f}$	550 V
				$I_{ss}$	140	140 mA	$U_f$	38,5 V
				$U_{ss}$	103	165 V	$U_f$	>31,5 V
 <p>The top diagram shows a diode symbol with terminals 'a' (anode) and 'k' (cathode). The bottom diagram shows a circular pinout with terminals 'f' (filament) and 'k' (cathode).</p>								
Diode Half-wave rectifier								





Type Application	Dimensions Base	Heating		Operational Data				Maximum Ratings		
		Static data								
4654	Size P 4	$U_f$	6,3 V	AF push-pull power amplifier, class AB				$U_{a0}$	1200 V	
		$I_f$	1,35 A					$U_{a1}$	400 V	400 V
		Indirect heating		$U_{g3}$	0 V	0 V	0 V	$W_a$	18 W	
		$U_a$	400 V	$U_{g2}$	425 V	425 V	400 V	$U_{g20}$	1000 V	
		$U_{g3}$	0 V	$U_{g1}$	-	-30 V	-33 V	$U_{g2}$	425 V	
		$U_{g2}$	425 V	$R_k$	315	-	- $\Omega$	$U_{g20}$	3 W	
		$U_{g1}$	-33 V	$I_{a0}$	2×45	2×27,5	2×26 mA	$W_{g2}$	10 W	
		$I_{a1}$	45 mA	$I_{a1}$	2×50	2×97	2×80 mA	$I_k$	120 mA	
		$I_{g2}$	5 mA	$I_{g20}$	2×5	2×3	2×2,5 mA	$U_{k/f}$	50 V	
		$S$	6 mA/V	$I_{g2}$	2×13	2×23	2×20 mA	$R_{g1}(k)$	0,7 M $\Omega$	
		$R_i$	30 k $\Omega$	$R_{1-a}$	10	5	10 k $\Omega$	$R_{1(p)}$	0,5 M $\Omega$	
		$I_{az}$	( $U_{g1} = -45$ ) <15 mA	$P_o$	25	52,5	69 W	$R_{k/f}$	10 k $\Omega$	
				$k$	4	3,5	5 %	<b>Capacitances</b>		
				$U_{g1 ef}$	18,5	22	22 V	$C_{g1}$	15,5 pF	
							$C_a$	10 pF		
							$C_{g1/a}$	<0,9 pF		



Power pentode  
AF power amplifier



Type Application	Dimensions Base	Heating		Operational Data	Maximum Ratings	
		Static data				
AD1N  	Size P 1	$U_f$	4 V	<b>AF power amplifier, class A</b>  $U_b$ 295 V $U_{g1}$ -45 V $I_a$ 60 mA $R_a$ 2300 $\Omega$ $R_k$ 750 $\Omega$ $P_o$ 4,2 W $U_{g1 ef}$ 30 V $k$ 5 %	$U_{a0}$ 550 V $U_a$ 250 V $W_a$ 15 W $I_k$ 90 mA $R_{g1}^{1)}$ 0,3 $M\Omega$ $R_{g1}^{2)}$ 0,7 $M\Omega$  1) $U_{g1}$ fixed 2) $U_{g1}$ automatic	<b>Capacitances</b>  $C_{g1}$ 14,4 pF $C_a$ 10 pF $C_{a/g1}$ 6,9 pF
		$I_f$	2 A			
$t_f$	16 s					
Indirect heating ●						
$U_a$	250 V					
$U_{g1}$	-45 V					
$I_a$	60 mA					
$S$	4,3 mA/V					
$R_i$	1035 $\Omega$					
$\mu$	4,4					
$I_{ax} (U_{g1} = -70 V)$	10 mA					
<b>AF push-pull power amplifier</b>						
$U_b$	295 V	$U_{a0}$ 550 V $U_a$ 250 V $W_a$ 15 W $I_k$ 90 mA $R_{g1}^{1)}$ 0,3 $M\Omega$ $R_{g1}^{2)}$ 0,7 $M\Omega$  1) $U_{g1}$ fixed 2) $U_{g1}$ automatic	<b>Capacitances</b>  $C_{g1}$ 14,4 pF $C_a$ 10 pF $C_{a/g1}$ 6,9 pF			
$R_k$	375 $\Omega$					
$R_{a-a'}$	4 $k\Omega$					
$I_{a0}$	2×60 mA					
$I_a$	2×64 mA					
$P_o$	9,5 W					
$U_{g1 ef}$	30 V					
$k$	1,5 %					
<b>Power triode</b>						
<b>AF power amplifier</b>						

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
EAA91 6B32	Size max Ø 19×48 mm	$U_f$	6,3 V	Half-wave rectifier			Each section	
		$I_f$	0,3 A					
		$I_f$	0,3 A	$R_o$	300 Ω	$I_{ss}$	9 mA	
		$U_f$	6,3 V	$I_{sp}$	9 mA	$I_{sp\ 1)}$	90 mA	
		Indirect heating		$I_{sp}$	54 mA	$W_a$	0,5 W	
		$U_a$	4 V	Full-wave rectifier			$U_{+k/f-}$	330 V
		$I_a$	>10 mA	$U_{a\ ef}$	2×150 V	$U_{-k/f+}$	150 V	
				$R_o$	2×300 Ω	$R_{k/f}$	20 kΩ	
				$C_N$	1 μF	$U_{di}$ ( $I_d \leq 0,3 \mu A$ )	-1,3 V	
				$R_z$	15 kΩ	$C_N$	8 μF	
				$U_{ss}$	130 V	$R_o$	>200 Ω	
				Capacitances			1) Max, 18 μs, max 18% of a cycle	
				$C_{aI/kI+s+f}$	2,2 pF			
				$C_{aII/kII+s+f}$	2,2 pF			
				$C_{kI/aI+s+f}$	3,3 pF			
				$C_{kII/aII+s+f}$	3,3 pF			
				$C_{aI/aII}$	<0,05 pF			



Twin diode with separate cathodes, AM, FM, demodulator, ratio detector, full-wave rectifier

Type Application	Dimensions Base	Heating		Operational Data			Maximum Ratings	
		Static data						
EF95 6F32	Size max Ø 19×45,2 mm	$U_f$	6,3 V	RF amplifier, class A			$U_{a0}$	320 V
		$I_f$	0,175 A	$U_a$	120	180 V	$U_a$	200 V
		Indirect heating		$U_{g2}$	120	120 V	$W_a$	1,7 W
		$U_a$	120 V	$R_k$	200	200 Ω	$U_{g20}$	320 V
		$U_{g2}$	120 V	$I_a$	7,5	7,7 mA	$U_{g2}$	150 V
		$R_k$	200 Ω	$I_{g2}$	2,5	2,5 mA	$W_{g2}$	0,5 W
		$I_a$	7,5 mA	S	5	5,1 mA/V	$I_k$	18 mA
		$I_{g2}$	<3,5 mA	$R_i$	0,34	0,69 MΩ	$R_{g1}$	1 MΩ
		S	5,2 mA/V	$Z_{g1}$ (f=50 Mc/s)	25	25 kΩ	$U_k/f$	100 V
		$\mu_{g2/g1}$	25	$R_{ekv}$	2	2 kΩ	$R_k/f$	20 kΩ
		$R_i$	>0,25 MΩ	RF amplifier, class A - triode connection			Capacitances	
				$U_a$	120	180 V	$C_{g1}$	4,5 pF
				$U_{g1}$	-2,65	-6 V	$C_a$	2,8 pF
				$R_k$	265	925 Ω	$C_{a/g1}$	<0,025 pF
				$I_a$	10	6,5 mA		
				S	6	3,5 mA/V		
				$R_i$	5	6,66 kΩ		
				$\mu$	30	23,3		
				$Z_{g1}$ (f=100 Mc/s)	9,5	kΩ		
				$R_{ekv}$	700	Ω		



RF high-slope pentode  
PF, IF, wideband  
amplifier

Table of receiving tube equivalents

TESLA	European designation	Marconi	CV number	Other makers
1AF33	DAF96	ZD17 1)	CV784 1)	1FD1, 1FD9 1), 1S5T
1AF34				1B2Π, 1B1Π 1), 3)
1F33	DF96	W17 1)	CV785 1)	1F3 1), 1T4T
1F34				1K2Π, 1K1Π 1), 3)
1H33		X17 1)	CV782 1)	1C1 1), 1R5T
1H34				1A2Π, 1A1Π 1), 3)
1H35	DK96			1AB6
1L33	DL91 1)		CV783 1)	1S4T
1NN41	OA160			
1Y32				1Z2
1Y32T				~1Z2
2NN41				1N51
3L31				3A4 1)
3NN41	OA50			1N34
4NN41				1N48
5NN41	OA55			1N38
6B32	EAA91, EB91	D77/D152	CV140, CV283	6D2, 6X2Π
6BC32	EBC91			6AV6
6CC10	ECC33	B65	CV1988	6SN7, 6H8C
6CC31	ECC91		CV858	6H15Π, 6J6
6CC41				6H2Π, 12AX7 2)
6CC42				6385, 2C51, 5760, 6H3Π
6F10			CV660	6AC7, 6Ж4
6F31	EF93	W727	CV454	6BA6, 6K4Π
6F32	EF95		CV850	6AK5, 6Ж1Π
6F32V				5654, 6AK5W, 6AK5WA
6F35				6AJ5
6F36				6AH6, 6Ж5Π
6H31	EK90	X727	CV453	6A2Π, 6BE6
6L10			CV1882	6AG7, 6Π9
6L31	EL90	N727	CV1862	6005, 6AQ5, 6Π1Π 4)
6L41			CV2129	5763
6L43				6CL6
6NN41				1N64
6Z31				6X4, 6Ц4Π

TESLA	European designation	Marconi	CV number	Other makers
7QR20	~DG7-6 4)			~3BP1, ~3QP1 4)
12BC32	HBC91			12AV6
12F31	HF93		CV1928	12BA6
12H31	HK90			12BE6
12QR50			CV1069 4)	5JP1 4)
12QR51				~OE411PAV 4)
25QP20				10BP4
25QP21				10BP7
251QQ44	A25-10W			
280QQ44	A28-13W			
470QQ44	AW47-91			19ALP4, 19AQP4, 19BEP4
472QQ44	A47-11W			
502QQ44	A50-12W			
590QQ44	AW59-90			23AJP4, 23AMP4, 23AQP4, 23BCP4
592QQ44	A59-12W/2, A59-11W			23DEP4, 23DRP4, 23FQP4 23HBP4
AZ1			CV2860	
DY86				1S2
E88CC				6922, CC $\alpha$
E180F				6608, 5A/170K, EF861
EAA91				6AL5
EABC80		DH719		6LD12, 6T8, 6AK8
EBF89				7125, 6DC8
EC86				6CM4
EC88				6DL4, 6LD4
ECC82		B329	CV491	12AU7
ECC83		B339	CV492	12AX7, 6L13
ECC84				6CW7, 6H14II
ECC85		B719		6L12, 6AQ8
ECC88				6DJ8, 6H23II
ECC91				6J6, 6H15II
ECC189				6ES8
ECC802S				12AU7WA, 6067
ECC803S				12AX7WA, 6057

TESLA	European designation	Marconi	CV number	Other makers
ECH81		X719	CV2128	6C12, 6AJ8, 6I1Π
ECH84				6JX8
ECF82				6U8
ECL82				6BM8
ECL84				6DX8
ECL86				6GW8
EF80		Z719, Z152		64SPT, 6BX6
EF86		Z729		6267, 6Ж32Π
EF89			CV2901	6DA6
EF183				6EH7, 6F29
EF184				6EJ7, 6F30
EF800				EF860
EF806S				6267
EL34				6CA7
EL36				6CM5
EL81			CV2721	6CJ6
EL82				6DY5
EL83			CV2726	6CK6, 6CN6
EL84		N709	CV2975	6P15, 6BQ5, 6Π14Π, 6L40
EL86				6CW5
EL500				6GB5A
EM4n			~CV1434	
EM80			CV1352	65ME, 6BR5, 6E1Π
EM81				6DA5
EM84				6FG6
EY82				6H3
EY83				6Ц10Π <sup>3)</sup>
EY88				6AL3
EY86				6S2
EZ80				6V4
EZ81		U709		UU12, 6CA4
PABC80				9AK8
PCC84				30L1, 7AN7
PC86				4CM4
PC88				4DL4
PCC85				9AQ8

<b>TESLA</b>	<b>European designation</b>	<b>Marconi</b>	<b>CV number</b>	<b>Other makers</b>
<b>PCC88</b>				7DJ8
<b>PCC189</b>				7ES8
<b>PCF82</b>				9U8
<b>PCF200</b>				8X9
<b>PCF801</b>				8GJ7
<b>PCF802</b>				8JW8
<b>PCL82</b>		~LN309		16A8, 30P12
<b>PCH200</b>				9V9
<b>PCL85</b>				18GV8
<b>PCL86</b>				14GW8
<b>PL36</b>				25E5, 30P4
<b>PL81</b>		N152, N359		213Pen, 21A6
<b>PL82</b>		N154, N329		30P16, 16A5
<b>PL83</b>		N153		15A6
<b>PL84</b>				30P18
<b>PL500</b>				28GB5
<b>PY82</b>		U152		19SU, 19Y3
<b>PY83</b>				17Z3
<b>PY88</b>				30AE3
<b>UABC80</b>				10LD12
<b>UBF89</b>				10FD12, 19DC8, 19FL8
<b>UCC85</b>				10L14
<b>UCH81</b>				10C14, 19D8, 19AJ8
<b>UCL82</b>				10PL12, 50BM8
<b>UL84</b>				10P18, 45B5
<b>UY85</b>				38A3
<b>UM80</b>				19BR5
<b>UY82</b>				55N3

1. Double heating current, TESLA type more economical
2. Different socket
3. Different heating voltage
4. Different external design